

## Projector Control Command Reference Manual Appendixes

This is the supplemental document to the principal. Please refer to the principal about detailed information including precautions.

### No.BDT140014

#### Revision History

Revision	Date	Description	Reference	Supported models
20.0	April 16, 2020	<p>Added the supported models.</p> <p>Corrected the error. "Input terminal" Modified Model name from NP-PH1005QL to NP-PX1005QL.</p>	7.1	<p>NP4100 / NP4100W NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X NP-ME360X / NP-ME310X / NP-ME270X NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X NP-P605UL / NP-P525UL / NP-P525WL NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X NP-P420X / NP-P350X / NP-P350W NP-PE401H <i>NP-PA1004UL / NP-PA804UL</i> NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U NP-PH3501QL / NP-PH2601QL NP-PH1400U NP-PH1202HL / NP-PH1002HL NP-PH1000U <i>NP-PX2000UL</i> NP-PX1005QL NP-PX1004UL NP-PX803UL NP-PX750U / NP-PX700W / NP-PX800X NP-PX651X / NP-PX581W NP-PX620X / NP-PX550W NP-PX602UL / NP-PX602WL NP-U321H NP-U300X / NP-U250X / NP-U310W / NP-U260W NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H NP-V311W / NP-V281W / NP-V311X NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R NP-VE303X / NP-VE303 NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>
				<p>NP4100 / NP4100W NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W</p>

19.0	September 30, 2019	Added the supported models.	7.0	<p>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /  NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X  NP-ME360X / NP-ME310X / NP-ME270X  NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /  NP-P603X / NP-P523X / NP-PE523X  <i>NP-P605UL</i> / NP-P525UL / NP-P525WL  NP-P502HL / NP-P502WL  NP-P502H / NP-P502W / NP-P452H / NP-P452W  NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X  NP-P420X / NP-P350X / NP-P350W  NP-PE401H  NP-PA803UL / NP-PA653UL  NP-PA803U / NP-PA723U / NP-PA653U /  NP-PA853W / NP-PA703W / NP-PA903X  NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /  NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /  NP-PA721X / NP-PA621X  NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U  NP-PH3501QL / NP-PH2601QL  NP-PH1400U  NP-PH1202HL / NP-PH1002HL  NP-PH1000U  NP-PX1005QL  NP-PX1004UL  NP-PX803UL  NP-PX750U / NP-PX700W / NP-PX800X  NP-PX651X / NP-PX581W  NP-PX620X / NP-PX550W  NP-PX602UL / NP-PX602WL  NP-U321H  NP-U300X / NP-U250X / NP-U310W / NP-U260W  NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W  NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W  NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H  NP-V311W / NP-V281W / NP-V311X  NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 /  NP-V230 / NP-V260R  NP-VE303X / NP-VE303  NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>
18.0	April 24, 2019	Added the supported models.	7.0	<p>NP4100 / NP4100W  NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X /  NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS /  NP-M260XS / NP-M300WS / NP-M260WS  NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W /  NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS /  NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS  NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X /  NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS  NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W  NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /  NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X  NP-ME360X / NP-ME310X / NP-ME270X  NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /  NP-P603X / NP-P523X / NP-PE523X  NP-P525UL / NP-P525WL  NP-P502HL / NP-P502WL  NP-P502H / NP-P502W / NP-P452H / NP-P452W  NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X  NP-P420X / NP-P350X / NP-P350W  NP-PE401H  NP-PA803UL / NP-PA653UL  NP-PA803U / NP-PA723U / NP-PA653U /  NP-PA853W / NP-PA703W / NP-PA903X  NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /  NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /  NP-PA721X / NP-PA621X  NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U  NP-PH3501QL / NP-PH2601QL  NP-PH1400U  NP-PH1202HL / NP-PH1002HL  NP-PH1000U  <i>NP-PX1005QL</i>  NP-PX1004UL  NP-PX803UL  NP-PX750U / NP-PX700W / NP-PX800X  NP-PX651X / NP-PX581W  NP-PX620X / NP-PX550W  NP-PX602UL / NP-PX602WL  NP-U321H  NP-U300X / NP-U250X / NP-U310W / NP-U260W</p>

				<p>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W  NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W  NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H  NP-V311W / NP-V281W / NP-V311X  NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 /  NP-V230 / NP-V260R  NP-VE303X / NP-VE303  NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>
17.0	March 27, 2019	Added the supported models.	7.0	<p>NP4100 / NP4100W  NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X /  NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS /  NP-M260XS / NP-M300WS / NP-M260WS  NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W /  NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS /  NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS  NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X /  NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS  NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W  NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /  NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X  NP-ME360X / NP-ME310X / NP-ME270X  NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /  NP-P603X / NP-P523X / NP-PE523X  NP-P525UL / NP-P525WL  NP-P502HL / NP-P502WL  NP-P502H / NP-P502W / NP-P452H / NP-P452W  NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X  NP-P420X / NP-P350X / NP-P350W  NP-PE401H  NP-PA803UL / NP-PA653UL  NP-PA803U / NP-PA723U / NP-PA653U /  NP-PA853W / NP-PA703W / NP-PA903X  NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /  NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /  NP-PA721X / NP-PA621X  NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U  NP-PH3501QL / NP-PH2601QL  NP-PH1400U  NP-PH1202HL / NP-PH1002HL  NP-PH1000U  NP-PX1004UL  NP-PX803UL  NP-PX750U / NP-PX700W / NP-PX800X  NP-PX651X / NP-PX581W  NP-PX620X / NP-PX550W  NP-PX602UL / NP-PX602WL  NP-U321H  NP-U300X / NP-U250X / NP-U310W / NP-U260W  NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W  NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W  NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H  NP-V311W / NP-V281W / NP-V311X  NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 /  NP-V230 / NP-V260R  NP-VE303X / NP-VE303  NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>
16.0	July 6, 2018	<p>Added the supported models.  Corrected the error.  "3. Supported Command List"  NP-PA803UL / NP-PA653UL  does NOT support the following  command.  037-3. FILTER USAGE  INFORMATION REQUEST</p>	7.0	<p>NP4100 / NP4100W  NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X /  NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS /  NP-M260XS / NP-M300WS / NP-M260WS  NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W /  NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS /  NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS  NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X /  NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS  NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W  NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /  NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X  NP-ME360X / NP-ME310X / NP-ME270X  NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /  NP-P603X / NP-P523X / NP-PE523X  NP-P502HL / NP-P502WL  NP-P502H / NP-P502W / NP-P452H / NP-P452W  NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X  NP-P420X / NP-P350X / NP-P350W  NP-PE401H  NP-PA803UL / NP-PA653UL  NP-PA803U / NP-PA723U / NP-PA653U /  NP-PA853W / NP-PA703W / NP-PA903X  NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /  NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /  NP-PA721X / NP-PA621X  NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U  NP-PH3501QL / NP-PH2601QL</p>

				<p>NP-PH1400U  NP-PH1202HL / NP-PH1002HL  NP-PH1000U  NP-PX1004UL  NP-PX803UL  NP-PX750U / NP-PX700W / NP-PX800X  NP-PX651X / NP-PX581W  NP-PX620X / NP-PX550W  NP-PX602UL / NP-PX602WL  NP-U321H  NP-U300X / NP-U250X / NP-U310W / NP-U260W  NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W  NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W  NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H  NP-V311W / NP-V281W / NP-V311X  NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R  NP-VE303X / NP-VE303  NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>
15.1	January 17, 2018	<p>Corrected the error.  ■ Selection signal type  078-3. INPUT STATUS  REQUEST  305-3. BASIC INFORMATION  REQUEST  Model name : NP-PA803UL /  NP-PA653UL  NP-PA803U / NP-PA723U / NP-  PA653U / NP-PA853W / NP-  PA703W / NP-PA903X  Input terminal : HDBaseT</p>	6.1	Same as Revision 15.0.
15.0	November 10, 2017	Added the supported models.	6.1	<p>NP4100 / NP4100W  NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X /  NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS /  NP-M260XS / NP-M300WS / NP-M260WS  NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W /  NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS /  NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS  NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X /  NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS  NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W  NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W /  NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X  NP-ME360X / NP-ME310X / NP-ME270X  NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X /  NP-P603X / NP-P523X / NP-PE523X  NP-P502HL / NP-P502WL  NP-P502H / NP-P502W / NP-P452H / NP-P452W  NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X  NP-P420X / NP-P350X / NP-P350W  NP-PE401H  <i>NP-PA803UL / NP-PA653UL</i>  NP-PA803U / NP-PA723U / NP-PA653U /  NP-PA853W / NP-PA703W / NP-PA903X  NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X /  NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W /  NP-PA721X / NP-PA621X  NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U  NP-PH1400U  NP-PH1202HL / NP-PH1002HL  NP-PH1000U  <i>NP-PX1004UL</i>  NP-PX803UL  NP-PX750U / NP-PX700W / NP-PX800X  NP-PX651X / NP-PX581W  NP-PX620X / NP-PX550W  NP-PX602UL / NP-PX602WL  NP-U321H  NP-U300X / NP-U250X / NP-U310W / NP-U260W  NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W  NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W  NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H  NP-V311W / NP-V281W / NP-V311X  NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 /  NP-V230 / NP-V260R  NP-VE303X / NP-VE303  NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>
				<p>NP4100 / NP4100W  NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X /  NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS /  NP-M260XS / NP-M300WS / NP-M260WS  NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W /  NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS /  NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS</p>

14.0	July 3, 2017	Added the supported models.	6.1	<p>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS</p> <p>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W</p> <p>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X</p> <p>NP-ME360X / NP-ME310X / NP-ME270X</p> <p><i>NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X</i></p> <p>NP-P502HL / NP-P502WL</p> <p>NP-P502H / NP-P502W / NP-P452H / NP-P452W</p> <p>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X</p> <p>NP-P420X / NP-P350X / NP-P350W</p> <p>NP-PE401H</p> <p>NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X</p> <p>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X</p> <p>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U</p> <p>NP-PH1400U</p> <p>NP-PH1202HL / NP-PH1002HL</p> <p>NP-PH1000U</p> <p>NP-PX803UL</p> <p>NP-PX750U / NP-PX700W / NP-PX800X</p> <p>NP-PX651X / NP-PX581W</p> <p>NP-PX620X / NP-PX550W</p> <p>NP-PX602UL / NP-PX602WL</p> <p>NP-U321H</p> <p>NP-U300X / NP-U250X / NP-U310W / NP-U260W</p> <p>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W</p> <p>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W</p> <p>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H</p> <p>NP-V311W / NP-V281W / NP-V311X</p> <p>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R</p> <p>NP-VE303X / NP-VE303</p> <p>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>
13.1	May 15, 2017	Updated the Reference number.	6.1	Same as Revision 13.0.
13.0	January 11, 2017	<p>Added the supported models.</p> <p>Added the following commands in sheet "3. Supported Command List".</p> <p>051. LENS MUTE ON (SHUTTER CLOSE)</p> <p>052. LENS MUTE OFF (SHUTTER OPEN)</p>	6.0	<p>NP4100 / NP4100W</p> <p>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS</p> <p>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS</p> <p>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS</p> <p>NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W</p> <p>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X</p> <p>NP-ME360X / NP-ME310X / NP-ME270X</p> <p>NP-P502HL / NP-P502WL</p> <p>NP-P502H / NP-P502W / NP-P452H / NP-P452W</p> <p>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X</p> <p>NP-P420X / NP-P350X / NP-P350W</p> <p>NP-PE401H</p> <p><i>NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X</i></p> <p>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X</p> <p>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U</p> <p>NP-PH1400U</p> <p>NP-PH1202HL / NP-PH1002HL</p> <p>NP-PH1000U</p> <p>NP-PX803UL</p> <p>NP-PX750U / NP-PX700W / NP-PX800X</p> <p>NP-PX651X / NP-PX581W</p> <p>NP-PX620X / NP-PX550W</p> <p>NP-PX602UL / NP-PX602WL</p> <p>NP-U321H</p> <p>NP-U300X / NP-U250X / NP-U310W / NP-U260W</p> <p>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W</p> <p>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W</p> <p>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H</p> <p>NP-V311W / NP-V281W / NP-V311X</p> <p>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R</p> <p>NP-VE303X / NP-VE303</p> <p>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>
				<p>NP4100 / NP4100W</p> <p>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS</p>

12.0	October 25, 2016	Added the supported models.	<p>5.0</p> <p>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS  NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS  NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W  <i>NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X</i>  NP-ME360X / NP-ME310X / NP-ME270X  NP-P502HL / NP-P502WL  NP-P502H / NP-P502W / NP-P452H / NP-P452W  NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X  NP-P420X / NP-P350X / NP-P350W  NP-PE401H  NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X  NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U  NP-PH1400U  NP-PH1202HL / NP-PH1002HL  NP-PH1000U  NP-PX803UL  NP-PX750U / NP-PX700W / NP-PX800X  NP-PX651X / NP-PX581W  NP-PX620X / NP-PX550W  NP-PX602UL / NP-PX602WL  NP-U321H  NP-U300X / NP-U250X / NP-U310W / NP-U260W  NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W  NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W  NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H  NP-V311W / NP-V281W / NP-V311X  NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R  NP-VE303X / NP-VE303  NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>
11.0	February 29, 2016	<p>Added the supported models.</p> <p>Corrected [Aspect] sheet. ("WIDE ZOOM" is enabled by the WXGA model, and "LETTERBOX" is enabled by a XGA model about M403 / M402 / UM351 Series.)</p>	<p>5.0</p> <p>NP4100 / NP4100W  NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS  NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS  NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS  NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W  NP-ME360X / NP-ME310X / NP-ME270X  NP-P502HL / NP-P502WL  NP-P502H / NP-P502W / NP-P452H / NP-P452W  NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X  NP-P420X / NP-P350X / NP-P350W  NP-PE401H  NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X  NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U  NP-PH1400U  NP-PH1202HL / NP-PH1002HL  NP-PH1000U  NP-PX803UL  NP-PX750U / NP-PX700W / NP-PX800X  NP-PX651X / NP-PX581W  NP-PX620X / NP-PX550W  NP-PX602UL / NP-PX602WL  NP-U321H  NP-U300X / NP-U250X / NP-U310W / NP-U260W  NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W  NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W  NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H  NP-V311W / NP-V281W / NP-V311X  NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R  <i>NP-VE303X / NP-VE303</i>  NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</p>
			<p><i>NP4100 / NP4100W</i>  <i>NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS</i>  NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS  NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS  NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W</p>

10.0	February 17, 2016	Added the supported models. (Added the models supported at Revision1.0)	5.0	<p><i>NP-ME360X / NP-ME310X / NP-ME270X</i></p> <p>NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W</p> <p><i>NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X</i></p> <p><i>NP-P420X / NP-P350X / NP-P350W</i></p> <p><i>NP-PE401H</i></p> <p>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X</p> <p><i>NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U</i></p> <p><i>NP-PH1400U</i></p> <p>NP-PH1202HL / NP-PH1002HL</p> <p><i>NP-PH1000U</i></p> <p>NP-PX803UL</p> <p><i>NP-PX750U / NP-PX700W / NP-PX800X</i></p> <p>NP-PX651X / NP-PX581W</p> <p><i>NP-PX620X / NP-PX550W</i></p> <p>NP-PX602UL / NP-PX602WL</p> <p>NP-U321H</p> <p><i>NP-U300X / NP-U250X / NP-U310W / NP-U260W</i></p> <p>NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X / NP-UM352W</p> <p><i>NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W</i></p> <p>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H</p> <p><i>NP-V311W / NP-V281W / NP-V311X</i></p> <p><i>NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 /</i> <i>NP-V230 / NP-V260R</i></p> <p><i>NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280</i></p>
9.0	January 6, 2016	Added the Copyright on all pages.	5.0	Same as Revision 8.0.
8.0	December 21, 2015	Added the supported models.	4.0	<p>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS</p> <p>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS</p> <p>NP-P502HL / NP-P502WL</p> <p>NP-P502H / NP-P502W / NP-P452H / NP-P452W</p> <p>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X</p> <p>NP-PH1202HL / NP-PH1002HL</p> <p>NP-PX651X / NP-PX581W</p> <p>NP-PX602UL / NP-PX602WL</p> <p>NP-PX803UL</p> <p>NP-U321H</p> <p>NP-UM301X / NP-UM301W / NP-UM361X / NP-UM351W / NP-UM352W</p> <p>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H</p>
7.0	December 11, 2015	Added the supported models.	4.0	<p>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS</p> <p>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS</p> <p>NP-P502HL / NP-P502WL</p> <p>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X</p> <p>NP-PH1202HL / NP-PH1002HL</p> <p>NP-PX651X / NP-PX581W</p> <p>NP-PX602UL / NP-PX602WL</p> <p>NP-PX803UL</p> <p>NP-U321H</p> <p>NP-UM301X / NP-UM301W / NP-UM361X / NP-UM351W / NP-UM352W</p> <p>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H</p>
6.0	September 28, 2015	Added the supported models.	3.0	<p>NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS</p> <p>NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS</p> <p>NP-P502HL / NP-P502WL</p> <p>NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X</p> <p>NP-PH1202HL / NP-PH1002HL</p> <p>NP-PX651X / NP-PX581W</p> <p>NP-PX602UL / NP-PX602WL</p> <p>NP-U321H</p> <p>NP-UM301X / NP-UM301W / NP-UM361X / NP-UM351W / NP-UM352W</p> <p>NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H</p>

5.0	August 7, 2015	Added the supported models.	3.0	NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X NP-PH1202HL / NP-PH1002HL NP-PX651X / NP-PX581W NP-PX602UL / NP-PX602WL NP-U321H NP-UM301X / NP-UM301W / NP-UM361X / NP-UM351W / NP-UM352W NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H
4.0	August 3, 2015	Added the supported models. Corrected [3. Supported Command List ] sheet. (NP-U321H : "024. ONSCREEN MUTE ON" command is not supported.)	3.0	NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X NP-PH1202HL / NP-PH1002HL NP-PX651X / NP-PX581W NP-PX602UL / NP-PX602WL NP-U321H NP-UM301X / NP-UM301W / NP-UM361X / NP-UM351W / NP-UM352W NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H
3.0	June 16, 2015	Added the supported command.	3.0	Same as Revision 2.0.
2.0	May 29, 2015	Changed the supported models. Added the supported commands.	2.0	NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X NP-PH1202HL / NP-PH1002HL NP-PX651X / NP-PX581W NP-PX602UL / NP-PX602WL NP-U321H NP-UM301X / NP-UM301W / NP-UM361X / NP-UM351W / NP-UM352W
1.0	August 22, 2014	First version	1.0	NP4100 / NP4100W NP-M420X / NP-M420XV / NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W NP-ME360X / NP-ME310X / NP-ME270X NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X NP-P420X / NP-P350X / NP-P350W NP-PE401H NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X / NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U NP-PH1400U NP-PH1000U NP-PX750U / NP-PX700W / NP-PX800X NP-PX620X / NP-PX550W NP-U300X / NP-U250X / NP-U310W / NP-U260W NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W NP-V311W / NP-V281W / NP-V311X NP-V300X / NP-V260X / NP-V300W / NP-V260W / NP-V230X / NP-V260 / NP-V230 / NP-V260R NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280

# Contents

---

<b>1. Connecting an External Device</b> .....	10
<b>2. Standby Mode setting for receiving commands</b> .....	11
<b>3. Supported Command List</b> .....	12
<b>4. Supplementary Information by Command</b>	
Input terminal .....	18
[018. INPUT SW CHANGE] .....	
Aspect .....	23
[030-12. ASPECT ADJUST] .....	
Eco mode .....	25
[097-8. ECO MODE REQUEST] .....	
[098-8. ECO MODE SET] .....	
Base model type .....	26
[078-1. SETTING REQUEST] .....	
[305-1. BASE MODEL TYPE REQUEST] .....	
Selection signal type .....	30
[078-3. INPUT STATUS REQUEST] .....	
[305-3. BASIC INFORMATION REQUEST] .....	
Sub input .....	36
[097-198. PIP/PICTURE BY PICTURE REQUEST] .....	
[098-198. PIP/PICTURE BY PICTURE SET] .....	
Audio Select .....	38
[319-10. AUDIO SELECT SET] .....	

# 1. Connecting an External Device

<Conventions>

○ : Supported

— : Not supported

## ■ Projector

Model name	Serial port					LAN port	Wireless LAN unit
	4800bps	9600bps	19200bps	38400bps	115200bps		
NP4100 / NP4100W	○	○	○	○	—	○	—
NP-M420X / NP-M420XV NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS	○	○	○	○	—	○	○
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS	○	○	○	○	—	○	○
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS	○	○	○	○	—	○	○
NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W	○	○	○	○	—	○	○
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X	○	○	○	○	—	○	○
NP-ME360X / NP-ME310X / NP-ME270X	○	○	○	—	—	—	—
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X	○	○	○	○	—	○	○
NP-P605UL / NP-P525UL / NP-P525WL	○	○	○	○	—	○	○
NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W	○	○	○	○	—	○	○
NP-P501X / NP-P451X / NP-P451W / NP-P401W	○	○	○	○	—	○	○
NP-P420X / NP-P350X / NP-P350W	○	○	○	○	—	○	○
NP-PE501X	○	○	○	○	—	—	—
NP-PE401H	—	—	—	○	—	○	—
NP-PA1004UL / NP-PA804UL	○	○	○	○	○	○	—
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X	○	○	○	○	○	○	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X	○	○	○	○	○	○	—
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X	○	○	○	○	○	○	○
NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U	○	○	○	○	○	○	○
NP-PH3501QL / NP-PH2601QL	○	○	○	○	○	○	—
NP-PH1400U	○	○	○	○	○	○	○
NP-PH1202HL / NP-PH1002HL	○	○	○	○	○	○	—
NP-PH1000U	○	○	○	○	○	○	○
NP-PX2000UL	—	○	—	—	—	○	—
NP-PX1005QL	○	○	○	○	○	○	—
NP-PX1004UL NP-PX803UL	○	○	○	○	○	○	—
NP-PX750U / NP-PX700W / NP-PX800X	○	○	○	○	○	○	○
NP-PX651X / NP-PX581W	—	○	○	○	—	○	—
NP-PX620X / NP-PX550W	○	○	○	○	—	○	—
NP-PX602UL / NP-PX602WL	○	○	○	○	○	○	—
NP-U321H	—	—	—	○	—	○	—
NP-U300X / NP-U250X / NP-U310W / NP-U260W	—	—	—	○	—	○	—
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X NP-UM352W	○	○	○	○	—	○	○
NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W	○	○	○	○	—	○	○
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H	—	—	—	○	—	○	—
NP-V311W / NP-V281W / NP-V311X	○	○	○	○	—	○	—
NP-V300X / NP-V260X / NP-V300W / NP-V260W	○	○	○	○	—	○	—
NP-V230X / NP-V260 / NP-V230 / NP-V260R	○	○	○	○	—	—	—
NP-VE303X / NP-VE303	—	—	—	○	—	—	—
NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280	○	○	○	○	—	—	—

## 2. Standby Mode setting for receiving commands

The Standby Mode setting that can receive commands is different depending on the model.

Please see the table below.

**Target command: "015. POWER ON"**

### ■ Projector

Model name	Setting of the Standby Mode	
	When connected using a serial cable	When connected using via a wired LAN
NP4100 / NP4100W	Normal	Normal
NP-M420X / NP-M420XV NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS	NORMAL, POWER-SAVING	NORMAL
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS	NORMAL, NETWORK STANDBY	NETWORK STANDBY
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS	NORMAL, NETWORK STANDBY	NETWORK STANDBY
NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W	NORMAL, POWER-SAVING	NORMAL
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X	NORMAL, NETWORK STANDBY	NETWORK STANDBY
NP-ME360X / NP-ME310X / NP-ME270X	NORMAL, POWER-SAVING	
NP-P54U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X	NORMAL, NETWORK STANDBY	NETWORK STANDBY
NP-P605UL / NP-P525UL / NP-P525WL	NORMAL, NETWORK STANDBY, SLEEP	NETWORK STANDBY, SLEEP
NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W	NORMAL, NETWORK STANDBY	NETWORK STANDBY
NP-P501X / NP-P451X / NP-P451W / NP-P401W	NORMAL, POWER-SAVING, NETWORK STANDBY	NORMAL, NETWORK STANDBY
NP-P420X / NP-P350X / NP-P350W	NORMAL, POWER-SAVING	NORMAL
NP-PE501X	NORMAL, POWER-SAVING	
NP-PE401H	NORMAL	NORMAL
NP-PA1004UL / NP-PA804UL	OFF, ON	OFF, ON
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X	NORMAL, SLEEP	NORMAL, SLEEP
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X	NORMAL, HTBaseT STANDBY	HTBaseT STANDBY
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X	NORMAL, NETWORK STANDBY	NETWORK STANDBY
NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U	NORMAL, POWER-SAVING, NETWORK STANDBY	NORMAL, NETWORK STANDBY
NP-PH1400U	NORMAL, POWER-SAVING, NETWORK STANDBY	NORMAL, NETWORK STANDBY
NP-PH1202HL / NP-PH1002HL	NORMAL, NETWORK STANDBY	NETWORK STANDBY
NP-PH1000U	NORMAL, POWER-SAVING, NETWORK STANDBY	NORMAL, NETWORK STANDBY
※ NP-PX2000UL	STANDBY POWER ON	STANDBY POWER ON
NP-PX1005QL	NORMAL, SLEEP	NORMAL, SLEEP
NP-PX1004UL NP-PX803UL	NORMAL, NETWORK STANDBY	NETWORK STANDBY
NP-PX750U / NP-PX700W / NP-PX800X	NORMAL, POWER-SAVING, NETWORK STANDBY	NORMAL, NETWORK STANDBY
NP-PX651X / NP-PX581W	NORMAL, NETWORK STANDBY	NETWORK STANDBY
NP-PX620X / NP-PX550W	Normal	Normal
NP-PX602UL / NP-PX602WL	NORMAL, NETWORK STANDBY	NETWORK STANDBY
NP-U321H	NORMAL, NETWORK STANDBY	NETWORK STANDBY
NP-U300X / NP-U250X / NP-U310W / NP-U260W	Normal	Normal
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X NP-UM352W	NORMAL, NETWORK STANDBY	NETWORK STANDBY
NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W	NORMAL, POWER-SAVING	NORMAL
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H	NORMAL, NETWORK STANDBY	NETWORK STANDBY
NP-V311W / NP-V281W / NP-V311X	NORMAL, POWER-SAVING	NORMAL
NP-V300X / NP-V260X / NP-V300W / NP-V260W	NORMAL, POWER-SAVING	NORMAL
NP-V230X / NP-V260 / NP-V230 / NP-V260R	NORMAL, POWER-SAVING	
NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280	NORMAL, POWER-SAVING	

※ The following models use a different menu item name.

· NP-PX2000UL: STANDBY POWER

### 3. Supported Command List

<Conventions>  
 ○ : Supported  
 - : Not supported

#### ■ Projector

Command	NP4100 NP4100W (firmware version 1.02 or later)	NP-M420X NP-M350X NP-M300X NP-M260X NP-M230X NP-M300W NP-M260W	NP-M420XV	NP-M403X NP-M363X NP-M323X NP-M283X NP-M403W NP-M363W NP-M323W NP-M333XS NP-M353WS NP-M303WS NP-M403H NP-M323H NP-M353HS NP-M323HS NP-M303HS	NP-M402W NP-M362W NP-M402X NP-M362X NP-M322X NP-M282X NP-M322W NP-M352WS NP-M302WS NP-M332XS	NP-M361X NP-M311X NP-M271X NP-M311W NP-M271W	NP-M350XS NP-M300XS NP-M260XS NP-M300WS NP-M260WS
009. ERROR STATUS REQUEST	○	○	○	○	○	○	○
015. POWER ON	○	○	○	○	○	○	○
016. POWER OFF	○	○	○	○	○	○	○
018. INPUT SW CHANGE	○	○	○	○	○	○	○
020. PICTURE MUTE ON	○	○	○	○	○	○	○
021. PICTURE MUTE OFF	○	○	○	○	○	○	○
022. SOUND MUTE ON	○	○	-	○	○	○	○
023. SOUND MUTE OFF	○	○	-	○	○	○	○
024. ONSCREEN MUTE ON	○	○	○	○	○	○	○
025. ONSCREEN MUTE OFF	○	-	-	○	○	-	-
030-1. PICTURE ADJUST	○	○	○	○	○	○	○
030-2. VOLUME ADJUST	○	○	-	○	○	○	○
030-12. ASPECT ADJUST	-	-	-	○	○	-	-
030-15. OTHER ADJUST	-	-	-	-	-	-	-
037. INFORMATION REQUEST	-	-	-	○	○	-	-
037-3. FILTER USAGE INFORMATION REQUEST	-	○	○	-	-	○	○
037-4. LAMP INFORMATION REQUEST 3	○	○	○	○	○	○	○
037-6. CARBON SAVINGS INFORMATION REQUEST	-	-	-	○	○	-	-
050. REMOTE KEY CODE	-	○	○	○	○	○	○
051. LENS MUTE ON (SHUTTER CLOSE)	-	-	-	-	-	-	-
052. LENS MUTE OFF (SHUTTER OPEN)	-	-	-	-	-	-	-
053. LENS CONTROL	-	-	-	-	-	-	-
053-1. LENS CONTROL REQUEST	-	-	-	-	-	-	-
053-2. LENS CONTROL 2	-	-	-	-	-	-	-
053-3. LENS MEMORY CONTROL	-	-	-	-	-	-	-
053-4. REFERENCE LENS MEMORY CONTROL	-	-	-	-	-	-	-
053-5. LENS MEMORY OPTION REQUEST	-	-	-	-	-	-	-
053-6. LENS MEMORY OPTION SET	-	-	-	-	-	-	-
053-7. LENS INFORMATION REQUEST	-	-	-	-	-	-	-
053-10. LENS PROFILE SET	-	-	-	-	-	-	-
053-11. LENS PROFILE REQUEST	-	-	-	-	-	-	-
060-1. GAIN PARAMETER REQUEST 3	○	-	-	-	-	-	-
078-1. SETTING REQUEST	-	-	-	○	○	-	-
078-2. RUNNING STATUS REQUEST	-	-	-	○	○	-	-
078-3. INPUT STATUS REQUEST	-	-	-	○	○	-	-
078-4. MUTE STATUS REQUEST	-	-	-	○	○	-	-
078-5. MODEL NAME REQUEST	-	-	-	○	○	-	-
078-6. COVER STATUS REQUEST	-	○	○	○	○	○	-
079. FREEZE CONTROL	○	○	○	○	○	○	○
084. INFORMATION STRING REQUEST	-	○	○	○	○	○	○
097-8. ECO MODE REQUEST	○	○	○	○	○	○	○
097-45. LAN PROJECTOR NAME REQUEST	-	○	○	○	○	○	○
097-155. LAN MAC ADDRESS STATUS REQUEST2	-	○	○	○	○	○	○
097-198. PIP/PICTURE BY PICTURE REQUEST	-	-	-	-	-	-	-
097-243-1. EDGE BLENDING MODE REQUEST	-	-	-	-	-	-	-
098-8. ECO MODE SET	-	-	-	○	○	-	-
098-45. LAN PROJECTOR NAME SET	-	○	○	○	○	○	○
098-198. PIP/PICTURE BY PICTURE SET	-	-	-	-	-	-	-
098-243-1. EDGE BLENDING MODE SET	-	-	-	-	-	-	-
305-1. BASE MODEL TYPE REQUEST	○	○	○	○	○	○	○
305-2. SERIAL NUMBER REQUEST	○	○	○	○	○	○	○
305-3. BASIC INFORMATION REQUEST	○	○	○	○	○	○	○
319-10. AUDIO SELECT SET	-	-	-	-	-	-	-

### 3. Supported Command List

<Conventions>  
 ○ : Supported  
 - : Not supported

#### ■ Projector

Command	NP-ME401W NP-ME361W NP-ME331W NP-ME301W NP-ME401X NP-ME361X NP-ME331X NP-ME301X	NP-ME360X NP-ME310X NP-ME270X	NP-P554U NP-P474U NP-P554W NP-P474W NP-P604X NP-P603X NP-P523X NP-PE523X	NP-P605UL NP-P525UL NP-P525WL	NP-P502HL NP-P502WL NP-P502H NP-P502W NP-P452H NP-P452W	NP-P501X NP-P451X NP-P451W NP-P401W	NP-P420X NP-P350X NP-P350W
009. ERROR STATUS REQUEST	○	○	○	○	○	○	○
015. POWER ON	○	○	○	○	○	○	○
016. POWER OFF	○	○	○	○	○	○	○
018. INPUT SW CHANGE	○	○	○	○	○	○	○
020. PICTURE MUTE ON	○	○	○	○	○	○	○
021. PICTURE MUTE OFF	○	○	○	○	○	○	○
022. SOUND MUTE ON	○	○	○	○	○	○	○
023. SOUND MUTE OFF	○	○	○	○	○	○	○
024. ONSCREEN MUTE ON	○	○	○	○	○	○	○
025. ONSCREEN MUTE OFF	-	-	-	-	○	-	-
030-1. PICTURE ADJUST	○	○	○	○	○	○	○
030-2. VOLUME ADJUST	○	○	○	○	○	○	○
030-12. ASPECT ADJUST	○	-	○	○	○	-	-
030-15. OTHER ADJUST	-	-	-	○	-	-	-
037. INFORMATION REQUEST	○	-	○	○	○	-	-
037-3. FILTER USAGE INFORMATION REQUEST	○	○	○	-	-	○	○
037-4. LAMP INFORMATION REQUEST 3	○	○	○	○	○	○	○
037-6. CARBON SAVINGS INFORMATION REQUEST	○	-	○	○	○	-	-
050. REMOTE KEY CODE	○	○	○	○	○	○	○
051. LENS MUTE ON (SHUTTER CLOSE)	-	-	-	-	-	-	-
052. LENS MUTE OFF (SHUTTER OPEN)	-	-	-	-	-	-	-
053. LENS CONTROL	-	-	-	-	-	-	-
053-1. LENS CONTROL REQUEST	-	-	-	-	-	-	-
053-2. LENS CONTROL 2	-	-	-	-	-	-	-
053-3. LENS MEMORY CONTROL	-	-	-	-	-	-	-
053-4. REFERENCE LENS MEMORY CONTROL	-	-	-	-	-	-	-
053-5. LENS MEMORY OPTION REQUEST	-	-	-	-	-	-	-
053-6. LENS MEMORY OPTION SET	-	-	-	-	-	-	-
053-7. LENS INFORMATION REQUEST	-	-	-	-	-	-	-
053-10. LENS PROFILE SET	-	-	-	-	-	-	-
053-11. LENS PROFILE REQUEST	-	-	-	-	-	-	-
060-1. GAIN PARAMETER REQUEST 3	○	-	○	○	-	-	-
078-1. SETTING REQUEST	○	-	○	○	○	-	-
078-2. RUNNING STATUS REQUEST	○	-	○	○	○	-	-
078-3. INPUT STATUS REQUEST	○	-	○	○	○	-	-
078-4. MUTE STATUS REQUEST	○	-	○	○	○	-	-
078-5. MODEL NAME REQUEST	○	-	○	○	○	-	-
078-6. COVER STATUS REQUEST	-	-	-	○	-	○	○
079. FREEZE CONTROL	○	○	○	○	○	○	○
084. INFORMATION STRING REQUEST	○	○	○	○	○	○	○
097-8. ECO MODE REQUEST	○	○	○	○	○	○	○
097-45. LAN PROJECTOR NAME REQUEST	○	-	○	○	○	○	○
097-155. LAN MAC ADDRESS STATUS REQUEST2	○	-	○	○	○	○	○
097-198. PIP/PICTURE BY PICTURE REQUEST	-	-	-	○	-	-	-
097-243-1. EDGE BLENDING MODE REQUEST	-	-	-	-	-	-	-
098-8. ECO MODE SET	○	-	○	○	○	-	-
098-45. LAN PROJECTOR NAME SET	○	-	○	○	○	○	○
098-198. PIP/PICTURE BY PICTURE SET	-	-	-	○	-	-	-
098-243-1. EDGE BLENDING MODE SET	-	-	-	-	-	-	-
305-1. BASE MODEL TYPE REQUEST	○	○	○	○	○	○	○
305-2. SERIAL NUMBER REQUEST	○	○	○	○	○	○	○
305-3. BASIC INFORMATION REQUEST	○	○	○	○	○	○	○
319-10. AUDIO SELECT SET	○	-	○	○(Ver. 2.00 or later)	○	-	-

### 3. Supported Command List

<Conventions>  
 ○ : Supported  
 - : Not supported

#### ■ Projector

Command	NP-PE501X	NP-PE401H	NP-PA1004UL NP-PA804UL	NP-PA803UL NP-PA653UL	NP-PA803U NP-PA723U NP-PA653U NP-PA853W NP-PA703W NP-PA903X	NP-PA622U NP-PA522U NP-PA672W NP-PA572W NP-PA722X NP-PA622X NP-PA621U NP-PA521U NP-PA671W NP-PA571W NP-PA721X NP-PA621X	NP-PA600X NP-PA500X NP-PA550W NP-PA500U
009. ERROR STATUS REQUEST	○	○	○	○	○	○	○
015. POWER ON	○	○	○	○	○	○	○
016. POWER OFF	○	○	○	○	○	○	○
018. INPUT SW CHANGE	○	○	○	○	○	○	○
020. PICTURE MUTE ON	○	○	○	○	○	○	○
021. PICTURE MUTE OFF	○	○	○	○	○	○	○
022. SOUND MUTE ON	○	○	○	○	○	○	○
023. SOUND MUTE OFF	○	○	○	○	○	○	○
024. ONSCREEN MUTE ON	○	○	○	○	○	○	○
025. ONSCREEN MUTE OFF	-	-	○	○	○	○	○
030-1. PICTURE ADJUST	○	○	○	○	○	○	○
030-2. VOLUME ADJUST	○	○	○	○	○	○	○
030-12. ASPECT ADJUST	-	-	○	○	○	○	-
030-15. OTHER ADJUST	-	-	○	○	○	○	-
037. INFORMATION REQUEST	-	-	○	○	○	○	-
037-3. FILTER USAGE INFORMATION REQUEST	○	○	-	-	○	○	○
037-4. LAMP INFORMATION REQUEST 3	○	○	○	○	○	○	○
037-6. CARBON SAVINGS INFORMATION REQUEST	-	-	○	○	○	○	-
050. REMOTE KEY CODE	○	○	○	○	○	○	○
051. LENS MUTE ON (SHUTTER CLOSE)	-	-	○	-	-	-	-
052. LENS MUTE OFF (SHUTTER OPEN)	-	-	○	-	-	-	-
053. LENS CONTROL	-	-	○	○	○	-	-
053-1. LENS CONTROL REQUEST	-	-	○	○	○	-	-
053-2. LENS CONTROL 2	-	-	○	○	○	-	-
053-3. LENS MEMORY CONTROL	-	-	○	○	○	-	-
053-4. REFERENCE LENS MEMORY CONTROL	-	-	○	○	○	-	-
053-5. LENS MEMORY OPTION REQUEST	-	-	○	○	○	-	-
053-6. LENS MEMORY OPTION SET	-	-	○	○	○	-	-
053-7. LENS INFORMATION REQUEST	-	-	○	○	○	-	-
053-10. LENS PROFILE SET	-	-	○	○	○	-	-
053-11. LENS PROFILE REQUEST	-	-	○	○	○	-	-
060-1. GAIN PARAMETER REQUEST 3	-	-	○	○	○	○	○
078-1. SETTING REQUEST	-	-	○	○	○	○	-
078-2. RUNNING STATUS REQUEST	-	-	○	○	○	○	-
078-3. INPUT STATUS REQUEST	-	-	○	○	○	○	-
078-4. MUTE STATUS REQUEST	-	-	○	○	○	○	-
078-5. MODEL NAME REQUEST	-	-	○	○	○	○	-
078-6. COVER STATUS REQUEST	○	○	-	-	-	-	-
079. FREEZE CONTROL	○	○	○	○	○	○	○
084. INFORMATION STRING REQUEST	○	-	○	○	○	○	○
097-8. ECO MODE REQUEST	○	○	○	○	○	○	○
097-45. LAN PROJECTOR NAME REQUEST	○	○	○	○	○	○	○
097-155. LAN MAC ADDRESS STATUS REQUEST2	○	○	○	○	○	○	○
097-198. PIP/PICTURE BY PICTURE REQUEST	-	-	○	○	○	○	-
097-243-1. EDGE BLENDING MODE REQUEST	-	-	○	○	○	○	-
098-8. ECO MODE SET	-	-	○	○	○	○	-
098-45. LAN PROJECTOR NAME SET	○	○	○	○	○	○	○
098-198. PIP/PICTURE BY PICTURE SET	-	-	○	○	○	○	-
098-243-1. EDGE BLENDING MODE SET	-	-	○	○	○	○	-
305-1. BASE MODEL TYPE REQUEST	○	○	○	○	○	○	○
305-2. SERIAL NUMBER REQUEST	○	-	○	○	○	○	○
305-3. BASIC INFORMATION REQUEST	○	○	○	○	○	○	○
319-10. AUDIO SELECT SET	-	-	○	○	○	○	-

### 3. Supported Command List

<Conventions>  
 ○ : Supported  
 - : Not supported

#### ■ Projector

Command	NP-PH3501QL NP-PH2601QL	NP-PH1400U	NP-PH1202HL NP-PH1002HL	NP-PH1000U	NP-PX2000UL	NP-PX1005QL	NP-PX1004UL NP-PX803UL
009. ERROR STATUS REQUEST	○	○	○	○	○	○	○
015. POWER ON	○	○	○	○	○	○	○
016. POWER OFF	○	○	○	○	○	○	○
018. INPUT SW CHANGE	○	○	○	○	○	○	○
020. PICTURE MUTE ON	○	○	○	○	○	○	○
021. PICTURE MUTE OFF	○	○	○	○	○	○	○
022. SOUND MUTE ON	-	-	-	-	-	-	-
023. SOUND MUTE OFF	-	-	-	-	-	-	-
024. ONSCREEN MUTE ON	○	○	○	○	○	○	○
025. ONSCREEN MUTE OFF	○	○	○	○	○	○	○
030-1. PICTURE ADJUST	○	○	○	○	○	○	○
030-2. VOLUME ADJUST	-	-	-	-	-	-	-
030-12. ASPECT ADJUST	○	-	○	-	○	○	○
030-15. OTHER ADJUST	○	-	○	-	○	○	○
037. INFORMATION REQUEST	○	-	○	-	○	○	○
037-3. FILTER USAGE INFORMATION REQUEST	○	○	○	○	-	-	-
037-4. LAMP INFORMATION REQUEST 3	○	○	○	○	○	○	○
037-6. CARBON SAVINGS INFORMATION REQUEST	-	-	○	-	-	○	○
050. REMOTE KEY CODE	○	○	○	○	○	○	○
051. LENS MUTE ON (SHUTTER CLOSE)	○	○	○	○	○	○	○
052. LENS MUTE OFF (SHUTTER OPEN)	○	○	○	○	○	○	○
053. LENS CONTROL	○	-	○	-	○	○	○
053-1. LENS CONTROL REQUEST	○	-	○	-	-	○	○
053-2. LENS CONTROL 2	○	-	○	-	-	○	○
053-3. LENS MEMORY CONTROL	○	-	○	-	○	○	○
053-4. REFERENCE LENS MEMORY CONTROL	○	-	○	-	○	○	○
053-5. LENS MEMORY OPTION REQUEST	○	-	○	-	-	○	○
053-6. LENS MEMORY OPTION SET	○	-	○	-	-	○	○
053-7. LENS INFORMATION REQUEST	○	-	○	-	-	○	○
053-10. LENS PROFILE SET	○	-	○	-	○	○	○
053-11. LENS PROFILE REQUEST	○	-	○	-	○	○	○
060-1. GAIN PARAMETER REQUEST 3	○	○	○	○	○	○	○
078-1. SETTING REQUEST	○	-	○	-	○	○	○
078-2. RUNNING STATUS REQUEST	○	-	○	-	○	○	○
078-3. INPUT STATUS REQUEST	○	-	○	-	○	○	○
078-4. MUTE STATUS REQUEST	○	-	○	-	○	○	○
078-5. MODEL NAME REQUEST	○	-	○	-	○	○	○
078-6. COVER STATUS REQUEST	-	○	○	○	-	-	○
079. FREEZE CONTROL	○	○	○	○	○	○	○
084. INFORMATION STRING REQUEST	○	○	○	○	-	○	○
097-8. ECO MODE REQUEST	-	○	○	○	○	○	○
097-45. LAN PROJECTOR NAME REQUEST	○	○	○	○	○	○	○
097-155. LAN MAC ADDRESS STATUS REQUEST2	○	○	○	○	○	○	○
097-198. PIP/PICTURE BY PICTURE REQUEST	○	-	○	-	-	○	○
097-243-1. EDGE BLENDING MODE REQUEST	○	-	○	-	○	○	○
098-8. ECO MODE SET	-	-	○	-	○	○	○
098-45. LAN PROJECTOR NAME SET	○	○	○	○	○	○	○
098-198. PIP/PICTURE BY PICTURE SET	○	-	○	-	-	○	○
098-243-1. EDGE BLENDING MODE SET	○	-	○	-	○	○	○
305-1. BASE MODEL TYPE REQUEST	○	○	○	○	○	○	○
305-2. SERIAL NUMBER REQUEST	○	○	○	○	○	○	○
305-3. BASIC INFORMATION REQUEST	○	○	○	○	○	○	○
319-10. AUDIO SELECT SET	-	-	-	-	-	-	-

### 3. Supported Command List

<Conventions>  
 ○ : Supported  
 - : Not supported

#### ■ Projector

Command	NP-PX750U NP-PX700W NP-PX800X	NP-PX651X NP-PX581W	NP-PX620X NP-PX550W	NP-PX602UL NP-PX602WL	NP-U321H	NP-U300X NP-U250X NP-U310W NP-U260W	NP-UM351W NP-UM301W NP-UM361X NP-UM301X NP-UM352W
009. ERROR STATUS REQUEST	○	○	○	○	○	○	○
015. POWER ON	○	○	○	○	○	○	○
016. POWER OFF	○	○	○	○	○	○	○
018. INPUT SW CHANGE	○	○	○	○	○	○	○
020. PICTURE MUTE ON	○	○	○	○	○	○	○
021. PICTURE MUTE OFF	○	○	○	○	○	○	○
022. SOUND MUTE ON	-	-	○	-	○	○	○
023. SOUND MUTE OFF	-	-	○	-	○	○	○
024. ONSCREEN MUTE ON	○	-	○	○	-	○	○
025. ONSCREEN MUTE OFF	○	-	○	○	-	-	-
030-1. PICTURE ADJUST	○	○	○	○	○	○	○
030-2. VOLUME ADJUST	-	-	○	-	○	○	○
030-12. ASPECT ADJUST	-	○	-	○	○	-	○
030-15. OTHER ADJUST	-	-	-	○	-	-	-
037. INFORMATION REQUEST	-	○	-	○	○	-	○
037-3. FILTER USAGE INFORMATION REQUEST	○	○	-	-	○	○	○
037-4. LAMP INFORMATION REQUEST 3	○	○	○	○	○	○	○
037-6. CARBON SAVINGS INFORMATION REQUEST	-	-	-	○	-	-	○
050. REMOTE KEY CODE	○	○	-	○	○	○	○
051. LENS MUTE ON (SHUTTER CLOSE)	○	-	-	○	-	-	-
052. LENS MUTE OFF (SHUTTER OPEN)	○	-	-	○	-	-	-
053. LENS CONTROL	-	○	-	○	-	-	-
053-1. LENS CONTROL REQUEST	-	-	-	-	-	-	-
053-2. LENS CONTROL 2	-	-	-	-	-	-	-
053-3. LENS MEMORY CONTROL	-	-	-	-	-	-	-
053-4. REFERENCE LENS MEMORY CONTROL	-	-	-	-	-	-	-
053-5. LENS MEMORY OPTION REQUEST	-	-	-	-	-	-	-
053-6. LENS MEMORY OPTION SET	-	-	-	-	-	-	-
053-7. LENS INFORMATION REQUEST	-	-	-	-	-	-	-
053-10. LENS PROFILE SET	-	-	-	-	-	-	-
053-11. LENS PROFILE REQUEST	-	-	-	-	-	-	-
060-1. GAIN PARAMETER REQUEST 3	○	-	○	○	-	-	-
078-1. SETTING REQUEST	-	○	-	○	○	-	○
078-2. RUNNING STATUS REQUEST	-	○	-	○	○	-	○
078-3. INPUT STATUS REQUEST	-	○	-	○	○	-	○
078-4. MUTE STATUS REQUEST	-	○	-	○	○	-	○
078-5. MODEL NAME REQUEST	-	○	-	○	○	-	○
078-6. COVER STATUS REQUEST	○	-	-	○	-	-	○
079. FREEZE CONTROL	○	○	○	○	○	○	○
084. INFORMATION STRING REQUEST	○	-	-	○	-	-	○
097-8. ECO MODE REQUEST	○	○	○	○	○	○	○
097-45. LAN PROJECTOR NAME REQUEST	○	-	-	○	○	○	○
097-155. LAN MAC ADDRESS STATUS REQUEST2	○	○	-	○	○	○	○
097-198. PIP/PICTURE BY PICTURE REQUEST	-	-	-	○	-	-	-
097-243-1. EDGE BLENDING MODE REQUEST	-	-	-	○	-	-	-
098-8. ECO MODE SET	-	○	-	○	○	-	○
098-45. LAN PROJECTOR NAME SET	○	-	-	○	○	○	○
098-198. PIP/PICTURE BY PICTURE SET	-	-	-	○	-	-	-
098-243-1. EDGE BLENDING MODE SET	-	-	-	○	-	-	-
305-1. BASE MODEL TYPE REQUEST	○	○	○	○	○	○	○
305-2. SERIAL NUMBER REQUEST	○	○	○	○	○	-	○
305-3. BASIC INFORMATION REQUEST	○	○	○	○	○	○	○
319-10. AUDIO SELECT SET	-	-	-	-	-	-	○

### 3. Supported Command List

<Conventions>  
 ○ : Supported  
 - : Not supported

#### ■ Projector

Command	NP-UM330X NP-UM280X NP-UM330W NP-UM280W	NP-V332X NP-V332W NP-V302X NP-V302W NP-V302H	NP-V311W NP-V281W NP-V311X	NP-V300X NP-V260X NP-V300W NP-V260W	NP-V230X NP-V260 NP-V230 NP-V260R	NP-VE303X NP-VE303	NP-VE281X NP-VE280X NP-VE281 NP-VE280
009. ERROR STATUS REQUEST	○	○	○	○	○	○	○
015. POWER ON	○	○	○	○	○	○	○
016. POWER OFF	○	○	○	○	○	○	○
018. INPUT SW CHANGE	○	○	○	○	○	○	○
020. PICTURE MUTE ON	○	○	○	○	○	○	○
021. PICTURE MUTE OFF	○	○	○	○	○	○	○
022. SOUND MUTE ON	○	○	○	○	○	○	○
023. SOUND MUTE OFF	○	○	○	○	○	○	○
024. ONSCREEN MUTE ON	○	-	○	○	○	-	○
025. ONSCREEN MUTE OFF	-	-	○	○	○	-	○
030-1. PICTURE ADJUST	○	○	○	○	○	○	○
030-2. VOLUME ADJUST	○	○	○	○	○	○	○
030-12. ASPECT ADJUST	-	○	-	-	-	○	-
030-15. OTHER ADJUST	-	-	-	-	-	-	-
037. INFORMATION REQUEST	-	○	-	-	-	○	-
037-3. FILTER USAGE INFORMATION REQUEST	○	-	-	-	-	-	-
037-4. LAMP INFORMATION REQUEST 3	○	○	○	○	○	○	○
037-6. CARBON SAVINGS INFORMATION REQUEST	-	-	-	-	-	-	-
050. REMOTE KEY CODE	○	○	○	○	○	○	○
051. LENS MUTE ON (SHUTTER CLOSE)	-	-	-	-	-	-	-
052. LENS MUTE OFF (SHUTTER OPEN)	-	-	-	-	-	-	-
053. LENS CONTROL	-	-	-	-	-	-	-
053-1. LENS CONTROL REQUEST	-	-	-	-	-	-	-
053-2. LENS CONTROL 2	-	-	-	-	-	-	-
053-3. LENS MEMORY CONTROL	-	-	-	-	-	-	-
053-4. REFERENCE LENS MEMORY CONTROL	-	-	-	-	-	-	-
053-5. LENS MEMORY OPTION REQUEST	-	-	-	-	-	-	-
053-6. LENS MEMORY OPTION SET	-	-	-	-	-	-	-
053-7. LENS INFORMATION REQUEST	-	-	-	-	-	-	-
053-10. LENS PROFILE SET	-	-	-	-	-	-	-
053-11. LENS PROFILE REQUEST	-	-	-	-	-	-	-
060-1. GAIN PARAMETER REQUEST 3	-	-	-	-	-	-	-
078-1. SETTING REQUEST	-	○	-	-	-	○	-
078-2. RUNNING STATUS REQUEST	-	○	-	-	-	○	-
078-3. INPUT STATUS REQUEST	-	○	-	-	-	○	-
078-4. MUTE STATUS REQUEST	-	○	-	-	-	○	-
078-5. MODEL NAME REQUEST	-	○	-	-	-	○	-
078-6. COVER STATUS REQUEST	-	-	-	-	-	-	-
079. FREEZE CONTROL	○	○	○	○	○	○	○
084. INFORMATION STRING REQUEST	○	-	-	-	-	-	○
097-8. ECO MODE REQUEST	○	○	○	○	○	○	○
097-45. LAN PROJECTOR NAME REQUEST	○	○	○	○	-	○	-
097-155. LAN MAC ADDRESS STATUS REQUEST2	○	○	○	○	-	-	-
097-198. PIP/PICTURE BY PICTURE REQUEST	-	-	-	-	-	-	-
097-243-1. EDGE BLENDING MODE REQUEST	-	-	-	-	-	-	-
098-8. ECO MODE SET	-	○	-	-	-	○	-
098-45. LAN PROJECTOR NAME SET	○	○	○	○	-	○	-
098-198. PIP/PICTURE BY PICTURE SET	-	-	-	-	-	-	-
098-243-1. EDGE BLENDING MODE SET	-	-	-	-	-	-	-
305-1. BASE MODEL TYPE REQUEST	○	○	○	○	○	○	○
305-2. SERIAL NUMBER REQUEST	○	○	○	○	○	○	○
305-3. BASIC INFORMATION REQUEST	○	○	○	○	○	○	○
319-10. AUDIO SELECT SET	-	-	-	-	-	○	-

## 4. Supplementary Information by Command

### 018. INPUT SW CHANGE

#### ■ Input terminal

Model name	Input Terminal					
	COMPUTER	COMPUTER2	COMPUTER3	BNC	VIDEO	BNC(CV)
NP4100 / NP4100W	01h	02h	1Ah	—	06h	—
NP-M420X / NP-M420XV NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS	01h	02h	—	—	06h	—
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS	01h	—	—	—	06h	—
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS	01h	—	—	—	06h	—
NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W	01h	02h	—	—	06h	—
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X	01h	—	—	—	06h	—
NP-ME360X / NP-ME310X / NP-ME270X	01h	02h	—	—	06h	—
NP-P603X / NP-P523X / NP-PE523X	01h	—	—	—	06h	—
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X	01h	—	—	—	06h	—
NP-P605UL / NP-P525UL / NP-P525WL	01h	—	—	—	—	—
NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W	01h	—	—	—	06h	—
NP-P501X / NP-P451X / NP-P451W / NP-P401W	01h	—	—	—	06h	—
NP-P420X / NP-P350X / NP-P350W	01h	02h	—	—	06h	—
NP-PE501X	01h	—	—	—	06h	—
NP-PE401H	01h	—	—	—	06h	—
NP-PA1004UL / NP-PA804UL	01h	—	—	—	—	—
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X	01h	—	—	—	—	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X	01h	—	—	02h	—	06h
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X	01h	—	—	02h	—	06h
NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U	01h	02h	03h	—	06h	—
NP-PH3501QL / NP-PH2601QL	—	—	—	—	—	—
NP-PH1400U	01h	02h	03h	—	06h	—
NP-PH1202HL / NP-PH1002HL	01h	—	—	02h	—	06h
NP-PH1000U	01h	02h	03h	—	06h	—
NP-PX2000UL	01h	—	—	02h	—	—
NP-PX1005QL	—	—	—	—	—	—
NP-PX1004UL NP-PX803UL	01h	—	—	02h	—	06h
NP-PX750U / NP-PX700W / NP-PX800X	01h	02h	03h	—	06h	—
NP-PX651X / NP-PX581W	01h	02h	9Ch	—	06h	—
NP-PX620X / NP-PX550W	01h	02h	1Ah	—	06h	—
NP-PX602UL / NP-PX602WL	01h	—	—	02h	—	06h
NP-U321H	01h	—	—	—	06h	—
NP-U300X / NP-U250X / NP-U310W / NP-U260W	01h	02h	—	—	06h	—
NP-UM352W	01h	—	—	—	06h	—
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X	01h	—	—	—	06h	—
NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W	01h	—	—	—	06h	—
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H	01h	—	—	—	06h	—
NP-V311W / NP-V281W / NP-V311X	01h	02h	—	—	06h	—
NP-V300X / NP-V260X / NP-V300W / NP-V260W	01h	02h	—	—	06h	—
NP-V230X / NP-V260 / NP-V230	01h	—	—	—	06h	—
NP-V260R	01h	—	—	—	06h	—
NP-VE303X / NP-VE303	01h	—	—	—	06h	—
NP-VE281X / NP-VE281	01h	—	—	—	06h	—
NP-VE280X / NP-VE280	01h	—	—	—	06h	—

## 4. Supplementary Information by Command

### 018. INPUT SW CHANGE

#### ■ Input terminal

Model name	Input Terminal					
	S-VIDEO	BNC(Y/C)	Component	HDMI	HDMI2	DisplayPort
NP4100 / NP4100W	0Bh	—	10h	—	—	—
NP-M420X / NP-M420XV NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS	0Bh	—	—	1Ah	—	—
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS	—	—	—	A1h	A2h	—
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS	—	—	—	A1h	A2h	—
NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W	0Bh	—	—	1Ah	—	—
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X	—	—	—	A1h	A2h	—
NP-ME360X / NP-ME310X / NP-ME270X	—	—	—	—	—	—
NP-P603X / NP-P523X / NP-PE523X	—	—	—	A1h	A2h	—
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X	—	—	—	A1h	A2h	—
NP-P605UL / NP-P525UL / NP-P525WL	—	—	—	A1h	A2h	—
NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W	—	—	—	A1h	A2h	—
NP-P501X / NP-P451X / NP-P451W / NP-P401W	0Bh	—	—	1Ah	1Bh	—
NP-P420X / NP-P350X / NP-P350W	0Bh	—	—	1Ah	—	—
NP-PE501X	0Bh	—	—	1Ah	1Bh	—
NP-PE401H	0Bh	—	—	1Ah	1Bh	—
NP-PA1004UL / NP-PA804UL	—	—	—	A1h	A2h	A6h
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X	—	—	—	A1h	A2h	A6h
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X	—	0Bh	—	A1h	A2h	A6h
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X	—	0Bh	—	A1h	A2h	A6h
NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U	0Bh	—	—	1Ah	—	1Bh
NP-PH3501QL / NP-PH2601QL	—	—	—	A1h	A2h	A6h
NP-PH1400U	0Bh	—	—	1Ah	—	1Bh
NP-PH1202HL / NP-PH1002HL	—	0Bh	—	A1h	—	A6h
NP-PH1000U	0Bh	—	—	1Ah	—	1Bh
NP-PX2000UL	—	—	—	A1h	A2h	A6h
NP-PX1005QL	—	—	—	A1h	A2h	A6h
NP-PX1004UL NP-PX803UL	—	0Bh	—	A1h	—	A6h
NP-PX750U / NP-PX700W / NP-PX800X	0Bh	—	—	1Ah	—	1Bh
NP-PX651X / NP-PX581W	0Bh	—	10h	A1h	—	—
NP-PX620X / NP-PX550W	0Bh	—	10h	—	—	—
NP-PX602UL / NP-PX602WL	—	0Bh	—	A1h	—	A6h
NP-U321H	—	—	—	A1h	A2h	—
NP-U300X / NP-U250X / NP-U310W / NP-U260W	0Bh	—	—	1Ah	—	—
NP-UM352W	—	—	—	A1h	A2h	—
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X	—	—	—	A1h	A2h	—
NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W	0Bh	—	—	1Ah	1Bh	—
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H	—	—	—	A1h	A2h	—
NP-V311W / NP-V281W / NP-V311X	0Bh	—	—	1Ah	—	—
NP-V300X / NP-V260X / NP-V300W / NP-V260W	0Bh	—	—	1Ah	—	—
NP-V230X / NP-V260 / NP-V230	0Bh	—	—	—	—	—
NP-V260R	0Bh	—	—	1Ah	—	—
NP-VE303X / NP-VE303	—	—	—	A1h	—	—
NP-VE281X / NP-VE281	—	—	—	1Ah	—	—
NP-VE280X / NP-VE280	—	—	—	—	—	—

## 4. Supplementary Information by Command

### 018. INPUT SW CHANGE

#### ■ Input terminal

Model name	Input terminal					
	DisplayPort2	SLOT	STEREO DVI	DVI-D	VIEWER	USB-A
NP4100 / NP4100W	—	—	—	—	—	—
NP-M420X / NP-M420XV NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS	—	—	—	—	1Fh	—
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS	—	—	—	—	—	1Fh
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS	—	—	—	—	—	1Fh
NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W	—	—	—	—	1Fh	—
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X	—	—	—	—	—	1Fh
NP-ME360X / NP-ME310X / NP-ME270X	—	—	—	—	—	—
NP-P603X / NP-P523X / NP-PE523X	—	—	—	—	—	1Fh
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X	—	—	—	—	—	1Fh
NP-P605UL / NP-P525UL / NP-P525WL	—	—	—	—	—	1Fh
NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W	—	—	—	—	—	—
NP-P501X / NP-P451X / NP-P451W / NP-P401W	—	—	—	—	1Fh	—
NP-P420X / NP-P350X / NP-P350W	—	—	—	—	1Fh	—
NP-PE501X	—	—	—	—	—	—
NP-PE401H	—	—	—	—	—	—
NP-PA1004UL / NP-PA804UL	—	—	—	—	—	—
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X	—	—	—	—	—	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X	—	—	—	—	—	—
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X	—	—	—	—	—	1Fh
NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U	—	—	—	—	1Fh	—
NP-PH3501QL / NP-PH2601QL	A7h	ABh	—	—	—	—
NP-PH1400U	—	1Ch	2Eh	—	1Fh	—
NP-PH1202HL / NP-PH1002HL	—	ABh	—	—	—	—
NP-PH1000U	—	1Ch	—	—	1Fh	—
NP-PX2000UL	—	—	—	9Ch	—	—
NP-PX1005QL	A7h	ABh	—	—	—	—
NP-PX1004UL NP-PX803UL	—	ABh	—	—	—	—
NP-PX750U / NP-PX700W / NP-PX800X	—	1Ch	—	—	1Fh	—
NP-PX651X / NP-PX581W	—	—	—	—	—	—
NP-PX620X / NP-PX550W	—	—	—	—	—	—
NP-PX602UL / NP-PX602WL	—	ABh	—	—	—	—
NP-U321H	—	—	—	—	—	—
NP-U300X / NP-U250X / NP-U310W / NP-U260W	—	—	—	—	—	—
NP-UM352W	—	—	—	—	—	—
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X	—	—	—	—	—	1Fh
NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W	—	—	—	—	1Fh	—
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H	—	—	—	—	—	—
NP-V311W / NP-V281W / NP-V311X	—	—	—	—	—	—
NP-V300X / NP-V260X / NP-V300W / NP-V260W	—	—	—	—	—	—
NP-V230X / NP-V260 / NP-V230	—	—	—	—	—	—
NP-V260R	—	—	—	—	—	—
NP-VE303X / NP-VE303	—	—	—	—	—	—
NP-VE281X / NP-VE281	—	—	—	—	—	—
NP-VE280X / NP-VE280	—	—	—	—	—	—

## 4. Supplementary Information by Command

### 018. INPUT SW CHANGE

#### ■ Input terminal

Model name	Input Terminal					
	NETWORK	LAN	ETHERNET	HDBaseT	SDI	SDI2
NP4100 / NP4100W	—	—	—	—	—	—
NP-M420X / NP-M420XV NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS	20h	—	—	—	—	—
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS	—	20h	—	—	—	—
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS	—	20h	—	—	—	—
NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W	20h	—	—	—	—	—
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X	—	20h	—	—	—	—
NP-ME360X / NP-ME310X / NP-ME270X	—	—	—	—	—	—
NP-P603X / NP-P523X / NP-PE523X	—	—	—	—	—	—
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X	—	—	—	BFh	—	—
NP-P605UL / NP-P525UL / NP-P525WL	—	20h	—	BFh	—	—
NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W	—	—	—	BFh	—	—
NP-P501X / NP-P451X / NP-P451W / NP-P401W	20h	—	—	—	—	—
NP-P420X / NP-P350X / NP-P350W	20h	—	—	—	—	—
NP-PE501X	—	—	—	—	—	—
NP-PE401H	—	—	—	—	—	—
NP-PA1004UL / NP-PA804UL	—	—	—	BFh	—	—
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X	—	—	—	BFh	—	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X	—	—	—	20h	—	—
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X	—	—	20h	—	—	—
NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U	20h	—	—	—	—	—
NP-PH3501QL / NP-PH2601QL	—	—	—	BFh	C4h	C5h
NP-PH1400U	20h	—	—	—	—	—
NP-PH1202HL / NP-PH1002HL	—	—	—	20h	—	—
NP-PH1000U	20h	—	—	—	—	—
NP-PX2000UL	—	—	—	—	C4h	—
NP-PX1005QL	—	—	—	BFh	C4h	C5h
NP-PX1004UL NP-PX803UL	—	—	—	20h	—	—
NP-PX750U / NP-PX700W / NP-PX800X	20h	—	—	—	—	—
NP-PX651X / NP-PX581W	—	—	—	20h	—	—
NP-PX620X / NP-PX550W	—	—	—	—	—	—
NP-PX602UL / NP-PX602WL	—	—	—	20h	—	—
NP-U321H	—	—	—	—	—	—
NP-U300X / NP-U250X / NP-U310W / NP-U260W	—	—	—	—	—	—
NP-UM352W	—	—	—	—	—	—
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X	—	20h	—	—	—	—
NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W	20h	—	—	—	—	—
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H	—	—	—	—	—	—
NP-V311W / NP-V281W / NP-V311X	—	—	—	—	—	—
NP-V300X / NP-V260X / NP-V300W / NP-V260W	—	—	—	—	—	—
NP-V230X / NP-V260 / NP-V230	—	—	—	—	—	—
NP-V260R	—	—	—	—	—	—
NP-VE303X / NP-VE303	—	—	—	—	—	—
NP-VE281X / NP-VE281	—	—	—	—	—	—
NP-VE280X / NP-VE280	—	—	—	—	—	—

## 4. Supplementary Information by Command

### 018. INPUT SW CHANGE

#### ■ Input terminal

Model name	Input Terminal				
	SDI3	SDI4	USB DISPLAY	USB-B	APPS
NP4100 / NP4100W	—	—	—	—	—
NP-M420X / NP-M420XV NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS	—	—	22h	—	—
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS	—	—	—	22h	—
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS	—	—	—	22h	—
NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W	—	—	22h	—	—
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X	—	—	—	22h	—
NP-ME360X / NP-ME310X / NP-ME270X	—	—	—	—	—
NP-P603X / NP-P523X / NP-PE523X	—	—	—	—	—
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X	—	—	—	—	—
NP-P605UL / NP-P525UL / NP-P525WL	—	—	—	—	—
NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W	—	—	—	—	23h
NP-P501X / NP-P451X / NP-P451W / NP-P401W	—	—	22h	—	—
NP-P420X / NP-P350X / NP-P350W	—	—	22h	—	—
NP-PE501X	—	—	22h	—	—
NP-PE401H	—	—	—	—	—
NP-PA1004UL / NP-PA804UL	—	—	—	—	—
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X	—	—	—	—	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X	—	—	—	—	—
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X	—	—	—	—	—
NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U	—	—	—	—	—
NP-PH3501QL / NP-PH2601QL	C6h	C7h	—	—	—
NP-PH1400U	—	—	—	—	—
NP-PH1202HL / NP-PH1002HL	—	—	—	—	—
NP-PH1000U	—	—	—	—	—
NP-PX2000UL	—	—	—	—	—
NP-PX1005QL	C6h	C7h	—	—	—
NP-PX1004UL NP-PX803UL	—	—	—	—	—
NP-PX750U / NP-PX700W / NP-PX800X	—	—	—	—	—
NP-PX651X / NP-PX581W	—	—	—	—	—
NP-PX620X / NP-PX550W	—	—	—	—	—
NP-PX602UL / NP-PX602WL	—	—	—	—	—
NP-U321H	—	—	—	—	—
NP-U300X / NP-U250X / NP-U310W / NP-U260W	—	—	—	—	—
NP-UM352W	—	—	—	22h	23h
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X	—	—	—	22h	—
NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W	—	—	22h	—	—
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H	—	—	—	—	—
NP-V311W / NP-V281W / NP-V311X	—	—	—	—	—
NP-V300X / NP-V260X / NP-V300W / NP-V260W	—	—	—	—	—
NP-V230X / NP-V260 / NP-V230	—	—	—	—	—
NP-V260R	—	—	—	—	—
NP-VE303X / NP-VE303	—	—	—	—	—
NP-VE281X / NP-VE281	—	—	—	—	—
NP-VE280X / NP-VE280	—	—	—	—	—

## 4. Supplementary Information by Command

### 030-12. ASPECT ADJUST

#### ■ Aspect

Model name	DATA01								
	00h	01h	02h		03h	04h	05h	06h	
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS	AUTO	WIDE ZOOM (XGA Model)	16:9		NATIVE	4:3	15:9	16:10	
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS	AUTO	WIDE ZOOM (XGA Model)	16:9		NATIVE	4:3	15:9	16:10	
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X	AUTO	WIDE ZOOM (XGA Model)	CHINEMA	16:9	NATIVE	4:3	15:9	16:10	
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X	AUTO	WIDE ZOOM (XGA Model)	CHINEMA	16:9	NATIVE	4:3	15:9	16:10	
NP-P605UL / NP-P525UL / NP-P525WL	AUTO	—	16:9		NATIVE	4:3	15:9	16:10	
NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W	AUTO	—	16:9		NATIVE	4:3	15:9	16:10	
NP-PA1004UL / NP-PA804UL	4:3 (WINDOWS)	LETTER BOX	WIDE SCREEN	16:9	—	—	—	FULL	
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X	4:3 (WINDOWS)	LETTER BOX	WIDE SCREEN	16:9	—	—	—	FULL	
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X	4:3 (WINDOWS)	LETTER BOX	WIDE SCREEN	16:9	—	—	—	ZOOM	FULL
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X	4:3 (WINDOWS)	LETTER BOX	WIDE SCREEN	16:9	—	—	—	ZOOM	FULL
NP-PH3501QL / NP-PH2601QL	4:3	LETTER BOX	WIDE SCREEN	16:9	—	—	—	FULL	
NP-PH1202HL / NP-PH1002HL	4:3 (WINDOWS)	LETTER BOX	WIDE SCREEN	16:9	—	—	—	ZOOM	FULL
NP-PX2000UL	—	—	16:9		—	4:3	—	16:10	
NP-PX1005QL	4:3	—	WIDE SCREEN	16:9	—	—	—	FULL	
NP-PX1004UL NP-PX803UL	4:3 (WINDOWS)	LETTER BOX	WIDE SCREEN	16:9	—	—	—	ZOOM	FULL
NP-PX651X / NP-PX581W	4:3	—	16:9		1.85:1	2.35:1	Auto	16:10	
NP-PX602UL / NP-PX602WL	4:3 (WINDOWS)	LETTER BOX	WIDE SCREEN	16:9	—	—	—	ZOOM	FULL
NP-U321H	AUTO	—	16:9		NATIVE	4:3	15:9	16:10	
NP-UM301X / NP-UM361X NP-UM301W / NP-UM351W / NP-UM352W	AUTO	WIDE ZOOM (XGA Model)	CHINEMA	16:9	NATIVE	4:3	15:9	16:10	
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H	AUTO	—	16:9		NATIVE	4:3	15:9	16:10	
NP-VE303X / NP-VE303	AUTO	—	16:9		NATIVE	4:3	15:9	16:10	

## 4. Supplementary Information by Command

### 030-12. ASPECT ADJUST

#### ■ Aspect

Model name	DATA01									
	07h	08h	0Bh	0Ch	0Dh	0Eh	0Fh	10h	11h	12h
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS	LETTER BOX (WXGA Model)	—	—	—	—	—	—	—	—	—
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS	LETTER BOX (WXGA Model)	—	—	—	—	—	—	—	—	—
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X	LETTERBOX (WXGA Model)	—	—	—	—	—	—	—	—	—
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X	LETTERBOX (WXGA Model)	—	—	—	—	—	—	—	—	—
NP-P605UL / NP-P525UL / NP-P525WL	LETTER BOX	—	—	—	—	—	—	—	—	—
NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W	LETTER BOX	—	—	—	—	—	—	—	—	—
NP-PA1004UL / NP-PA804UL	ZOOM	—	5:4	16:10	15:9	NATIVE	AUTO	NORMAL	—	—
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X	ZOOM	—	5:4	16:10	15:9	NATIVE	AUTO	NORMAL	—	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X	—	—	5:4	16:10	15:9	NATIVE	AUTO	—	—	—
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X	—	—	5:4	16:10	15:9	NATIVE	AUTO	—	—	—
NP-PH3501QL / NP-PH2601QL	ZOOM	—	5:4	16:10	15:9	NATIVE	AUTO	NORMAL	—	—
NP-PH1202HL / NP-PH1002HL	—	—	5:4	16:10	15:9	NATIVE	AUTO	—	—	—
NP-PX2000UL	LETTER BOX	—	5:4	—	—	NATIVE	AUTO	—	1.88	2.35
NP-PX1005QL	ZOOM	—	5:4	16:10	15:9	NATIVE	AUTO	NORMAL	—	—
NP-PX1004UL NP-PX803UL	—	—	5:4	16:10	15:9	NATIVE	AUTO	—	—	—
NP-PX651X / NP-PX581W	—	—	5:4	16:10	—	Native	Auto	—	—	—
NP-PX602UL / NP-PX602WL	—	—	5:4	16:10	15:9	NATIVE	AUTO	—	—	—
NP-U321H	—	5:4	—	—	—	—	—	—	—	—
NP-UM301X / NP-UM361X NP-UM301W / NP-UM351W / NP-UM352W	LETTERBOX (WXGA Model)	—	—	—	—	—	—	—	—	—
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H	—	5:4	—	—	—	—	—	—	—	—
NP-VE303X / NP-VE303	—	5:4	—	—	—	—	—	—	—	—

## 4. Supplementary Information by Command

### 097-8. ECO MODE REQUEST

### 098-8. ECO MODE SET

#### ■ Eco mode

Model name	DATA01					
	00h	01h	02h	03h	04h	05h
* NP4100 / NP4100W	Normal	Eco	—	—	—	—
NP-M420X / NP-M420XV NP-M350X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M300WS / NP-M260WS	OFF	AUTO ECO	ECO1	—	—	—
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS	OFF	AUTO ECO	NORMAL	ECO	—	—
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS	OFF	AUTO ECO	NORMAL	ECO	—	—
NP-M300X / NP-M260X / NP-M260XS	OFF	AUTO ECO	ECO1	ECO2	—	—
NP-M361X / NP-M311X / NP-M271X / NP-M311W / NP-M271W	OFF	AUTO ECO	NORMAL	ECO	—	—
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X	OFF	AUTO ECO	NORMAL	ECO	—	—
NP-ME360X / NP-ME310X / NP-ME270X	OFF	ON	—	—	—	—
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X / NP-P603X / NP-P523X / NP-PE523X	OFF	AUTO ECO	NORMAL	ECO	—	—
NP-P605UL / NP-P525UL / NP-P525WL	OFF	—	—	ECO	LONG LIFE	—
NP-P502HL / NP-P502WL	OFF	ECO1	ECO2	—	—	—
NP-P502H / NP-P502W / NP-P452H / NP-P452W	OFF	AUTO ECO	NORMAL	ECO	—	—
NP-P501X / NP-P451X / NP-P451W / NP-P401W / NP-PE501X	OFF	AUTO ECO	NORMAL	ECO	—	—
NP-P420X / NP-P350X / NP-P350W	OFF	AUTO ECO	ECO1	—	—	—
NP-PE401H	OFF	ECO	—	—	—	—
NP-PA1004UL / NP-PA804UL	NORMAL	—	ECO1	ECO2	—	BOOST
NP-PA803UL / NP-PA653UL	NORMAL	—	ECO1	ECO2	LONG LIFE	—
NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X	OFF	ON	—	—	—	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X	OFF	ON	—	—	—	—
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X	OFF	ON	—	—	—	—
NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U	OFF	ON	—	—	—	—
NP-PH1400U	OFF	ON	—	—	—	—
NP-PH1202HL / NP-PH1002HL	NORMAL	—	ECO1	ECO2	LONG LIFE	—
NP-PH1000U	OFF	ON	—	—	—	—
NP-PX2000UL	NORMAL	—	ECO	—	—	BOOST
NP-PX1005QL	NORMAL	—	ECO1	ECO2	—	—
NP-PX1004UL NP-PX803UL	NORMAL	—	ECO1	ECO2	—	—
NP-PX750U / NP-PX700W / NP-PX800X	OFF	ON	—	—	—	—
NP-PX651X / NP-PX581W	NORMAL	ECO	—	—	—	—
* NP-PX620X / NP-PX550W	Normal	Eco	—	—	—	—
NP-PX602UL / NP-PX602WL	NORMAL	—	ECO1	ECO2	—	—
NP-U321H	OFF	ECO	—	—	—	—
NP-U300X / NP-U250X / NP-U310W / NP-U260W	OFF	ON	—	—	—	—
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X NP-UM352W	OFF	AUTO ECO	NORMAL	ECO	—	—
NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W	OFF	AUTO ECO	NORMAL	ECO	—	—
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H	OFF	ECO	—	—	—	—
NP-V311W / NP-V281W / NP-V311X	OFF	ON	—	—	—	—
NP-V300X / NP-V260X / NP-V230X / NP-V260 / NP-V230 / NP-V260R NP-V300W / NP-V260W	OFF	ON	—	—	—	—
NP-VE303X / NP-VE303	OFF	ECO	—	—	—	—
NP-VE281X / NP-VE280X / NP-VE281 / NP-VE280	OFF	ON	—	—	—	—

\* The following models use a different menu item name.

- NP4100 / NP4100W : Lamp Mode
- NP-PX620X / NP-PX550W : Lamp Mode

## 4. Supplementary Information by Command

### 078-1. SETTING REQUEST

### 305-1. BASE MODEL TYPE REQUEST

The asterisked models exclusively support "305-1. BASE MODEL TYPE REQUEST", i.e. don't support "078-1. SETTING REQUEST".

#### ■ Base model type

Model name	078-1. SETTING REQUEST			
	DATA01	DATA02	DATA03	
	305-1. BASE MODEL TYPE REQUEST			
	DATA01	DATA02	DATA12	DATA13
* NP4100	03h	08h	00h	10h
* NP4100W	03h	08h	01h	10h
* NP-M230X	FFh	13h	09h	10h
* NP-M260W	FFh	13h	06h	10h
* NP-M260WS	FFh	13h	08h	10h
* NP-M260X	FFh	13h	05h	10h
* NP-M260XS	FFh	13h	07h	10h
* NP-M271W	FFh	13h	04h	13h
* NP-M271X	FFh	13h	02h	13h
NP-M282X	FFh	22h	03h	10h
NP-M283X	FFh	22h	03h	12h
* NP-M300W	FFh	13h	02h	10h
* NP-M300WS	FFh	13h	04h	10h
* NP-M300X	FFh	13h	01h	10h
* NP-M300XS	FFh	13h	03h	10h
NP-M302WS	FFh	22h	09h	10h
NP-M303HS	FFh	22H	04H	11H
NP-M303WS	FFh	22h	09h	12h
* NP-M311W	FFh	13h	01h	13h
* NP-M311X	FFh	13h	03h	13h
NP-M322H	FFh	22h	01h	11h
NP-M322W	FFh	22h	06h	10h
NP-M322X	FFh	22h	02h	10h
NP-M323H	FFh	22h	0Bh	12h
NP-M323HS	FFh	22H	03H	11H
NP-M323W	FFh	22h	06h	12h
NP-M323X	FFh	22h	02h	12h
NP-M332XS	FFh	22h	07h	10h
NP-M333XS	FFh	22h	07h	12h
* NP-M350X	FFh	13h	00h	10h
* NP-M350XS	FFh	13h	0Ch	10h
NP-M352WS	FFh	22h	08h	10h
NP-M353HS	FFh	22H	02H	11H
NP-M353WS	FFh	22h	08h	12h
* NP-M361X	FFh	13h	00h	13h
NP-M362W	FFh	22h	05h	10h
NP-M362X	FFh	22h	01h	10h
NP-M363W	FFh	22h	05h	12h
NP-M363X	FFh	22h	01h	12h
NP-M402H	FFh	22h	00h	11h

## 4. Supplementary Information by Command

### 078-1. SETTING REQUEST

### 305-1. BASE MODEL TYPE REQUEST

The asterisked models exclusively support "305-1. BASE MODEL TYPE REQUEST", i.e. don't support "078-1. SETTING REQUEST".

#### ■ Base model type

Model name	078-1. SETTING REQUEST			
	DATA01	DATA02	DATA03	
	305-1. BASE MODEL TYPE REQUEST			
	DATA01	DATA02	DATA12	DATA13
NP-M402W	FFh	22h	04h	10h
NP-M402X	FFh	22h	00h	10h
NP-M403H	FFh	22h	0Ah	12h
NP-M403W	FFh	22h	04h	12h
NP-M403X	FFh	22h	00h	12h
* NP-M420X	FFh	13h	0Ah	10h
* NP-M420XV	FFh	13h	0Bh	10h
* NP-ME270X	FFh	10h	02h	13h
NP-ME301W	FFh	20H	05H	14H
NP-ME301X	FFh	20H	04H	14H
* NP-ME310X	FFh	10h	01h	13h
NP-ME331W	FFh	20H	03H	14H
NP-ME331X	FFh	20H	02H	14H
* NP-ME360X	FFh	10h	00h	13h
NP-ME361W	FFh	20H	01H	14H
NP-ME361X	FFh	20H	00H	14H
* NP-P350W	FFh	13h	02h	11h
* NP-P350X	FFh	13h	01h	11h
* NP-P401W	FFh	20h	03h	10h
* NP-P420X	FFh	13h	00h	11h
* NP-P451W	FFh	20h	02h	10h
* NP-P451X	FFh	20h	01h	10h
NP-P452H	FFh	22H	02H	14H
NP-P452W	FFh	22H	03H	14H
NP-P474U	FFh	20H	0AH	15H
NP-P474W	FFh	20H	01H	15H
* NP-P501X	FFh	20h	00h	10h
NP-P502H	FFh	22H	00H	14H
NP-P502HL	FFh	22h	00h	13h
NP-P502W	FFh	22H	01H	14H
NP-P502WL	FFh	22h	01h	13h
NP-P523X	FFh	20H	04H	15H
NP-P525UL	FFh	32H	00H	10H
NP-P525WL	FFh	32h	01h	10h
NP-P554U	FFh	20H	09H	15H
NP-P554W	FFh	20H	00H	15H
NP-P603X	FFh	20H	03H	15H
NP-P604X	FFh	20H	02H	15H
NP-P605UL	FFh	32H	02H	10H
* NP-PA500U	FFh	15h	03h	10h

## 4. Supplementary Information by Command

### 078-1. SETTING REQUEST

### 305-1. BASE MODEL TYPE REQUEST

The asterisked models exclusively support "305-1. BASE MODEL TYPE REQUEST", i.e. don't support "078-1. SETTING REQUEST".

#### ■ Base model type

Model name	078-1. SETTING REQUEST			
	DATA01	DATA02	DATA03	
	305-1. BASE MODEL TYPE REQUEST			
	DATA01	DATA02	DATA12	DATA13
* NP-PA500X	FFh	15h	01h	10h
NP-PA521U	FFh	21h	01h	10h
NP-PA522U	FFh	21h	01h	11h
* NP-PA550W	FFh	15h	02h	10h
NP-PA571W	FFh	21h	03h	10h
NP-PA572W	FFh	21h	03h	11h
* NP-PA600X	FFh	15h	00h	10h
NP-PA621U	FFh	21h	00h	10h
NP-PA621X	FFh	21h	05h	10h
NP-PA622U	FFh	21h	00h	11h
NP-PA622X	FFh	21h	05h	11h
NP-PA653U	FFh	2Eh	02h	10h
NP-PA653UL	FFh	2Eh	00h	11h
NP-PA671W	FFh	21h	02h	10h
NP-PA672W	FFh	21h	02h	11h
NP-PA703W	FFh	2Eh	05h	10h
NP-PA721X	FFh	21h	04h	10h
NP-PA722X	FFh	21h	04h	11h
NP-PA723U	FFh	2Eh	01h	10h
NP-PA803U	FFh	2Eh	00h	10h
NP-PA803UL	FFh	2Eh	01h	11h
NP-PA804UL	FFh	34h	01H	10H
NP-PA853W	FFh	2Eh	03h	10h
NP-PA903X	FFh	2Eh	06h	10h
NP-PA1004UL	FFh	34h	00h	10h
* NP-PE401H	FFh	14h	00h	11h
* NP-PE501X	FFh	20h	04h	10h
NP-PE523X	FFh	20H	05H	15H
* NP-PH1000U	FFh	19h	00h	10h
NP-PH1002HL	FFh	26h	01h	10h
NP-PH1202HL	FFh	26h	00h	10h
* NP-PH1400U	FFh	19h	00h	11h
NP-PH2601QL	FFh	30h	01h	10h
NP-PH3501QL	FFh	30h	00h	10h
* NP-PX550W	03h	08h	01h	11h
NP-PX581W	FFh	27h	01h	10h
NP-PX602UL	FFh	25h	00h	10h
NP-PX602WL	FFh	25h	01h	10h
* NP-PX620X	03h	08h	00h	11h
NP-PX651X	FFh	27h	00h	10h
* NP-PX700W	FFh	17h	01h	10h
* NP-PX750U	FFh	17h	00h	10h
* NP-PX800X	FFh	17h	02h	10h
NP-PX803UL	FFh	2Ch	00h	10h
NP-PX1004UL	FFh	2Fh	00h	10h

## 4. Supplementary Information by Command

### 078-1. SETTING REQUEST

### 305-1. BASE MODEL TYPE REQUEST

The asterisked models exclusively support "305-1. BASE MODEL TYPE REQUEST", i.e. don't support "078-1. SETTING REQUEST".

#### ■ Base model type

Model name	078-1. SETTING REQUEST			
	DATA01	DATA02	DATA03	
	305-1. BASE MODEL TYPE REQUEST			
	DATA01	DATA02	DATA12	DATA13
NP-PX1005QL	FFh	31h	00h	10h
NP-PX2000UL	FFh	35h	00h	10h
* NP-U250X	FFh	14h	01h	10h
* NP-U260W	FFh	14h	03h	10h
* NP-U300X	FFh	14h	02h	10h
* NP-U310W	FFh	14h	04h	10h
NP-U321H	FFh	28h	00h	10h
* NP-UM280W	FFh	13h	02h	12h
* NP-UM280X	FFh	13h	01h	12h
NP-UM301W	FFh	20h	02h	11h
NP-UM301X	FFh	20h	00h	11h
* NP-UM330W	FFh	13h	03h	12h
* NP-UM330X	FFh	13h	00h	12h
NP-UM351W	FFh	20h	03h	11h
NP-UM352W	FFh	20h	04h	11h
NP-UM361X	FFh	20h	01h	11h
* NP-V230	FFh	16h	04h	10h
* NP-V230X	FFh	16h	02h	10h
* NP-V260	FFh	16h	03h	10h
* NP-V260R	FFh	16h	07h	10h
* NP-V260W	FFh	16h	06h	10h
* NP-V260X	FFh	16h	01h	10h
* NP-V281W	FFh	16h	09h	10h
* NP-V300W	FFh	16h	05h	10h
* NP-V300X	FFh	16h	00h	10h
NP-V302H	FFh	2Ah	04h	10h
NP-V302W	FFh	2Ah	03h	10h
NP-V302X	FFh	2Ah	02h	10h
* NP-V311W	FFh	16h	08h	10h
* NP-V311X	FFh	16h	0Ah	10h
NP-V332W	FFh	2Ah	01h	10h
NP-V332X	FFh	2Ah	00h	10h
* NP-VE280	FFh	16h	05h	11h
* NP-VE280X	FFh	16h	02h	11h
* NP-VE281	FFh	16h	04h	11h
* NP-VE281X	FFh	16h	01h	11h
NP-VE303	FFh	2Bh	01h	10h
NP-VE303X	FFh	2Bh	00h	10h

## 4. Supplementary Information by Command

### 078-3. INPUT STATUS REQUEST 305-3. BASIC INFORMATION REQUEST

The asterisked models exclusively support "305-3. BASIC INFORMATION REQUEST",  
i.e. don't support "078-3. INPUT STATUS REQUEST".

#### ■ Selection signal type

Model name	DATA03	01h	01h	01h	01h	01h
	DATA04	01h	02h	03h	06h	07h
* NP4100 / NP4100W		Computer1	Video	S-Video	Computer3	—
NP-M420X / NP-M420XV NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS		COMPUTER1	VIDEO	S-VIDEO	HDMI	VIEWER
* NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS		COMPUTER	VIDEO	—	—	USB-A
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS		COMPUTER	VIDEO	—	—	USB-A
* NP-M361W / NP-M311X / NP-M271X / NP-M311W / NP-M271W		COMPUTER1	VIDEO	S-VIDEO	HDMI	VIEWER
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X		COMPUTER	VIDEO	—	—	USB-A
* NP-ME360X / NP-ME310X / NP-ME270X		COMPUTER1	VIDEO	—	—	—
NP-P603X / NP-P523X / NP-PE523X		COMPUTER	VIDEO	—	—	USB-A
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X		COMPUTER	VIDEO	—	—	USB-A
NP-P605UL / NP-P525UL / NP-P525WL		COMPUTER	—	—	—	USB-A
NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W		COMPUTER	VIDEO	—	—	—
* NP-P501X / NP-P451X / NP-P451W / NP-P401W		COMPUTER	VIDEO	S-VIDEO	HDMI1	VIEWER
* NP-P420X / NP-P350X / NP-P350W		COMPUTER1	VIDEO	S-VIDEO	HDMI	VIEWER
* NP-PE501X		COMPUTER	VIDEO	S-VIDEO	HDMI1	—
* NP-PE401H		COMPUTER	VIDEO	S-VIDEO	HDMI1	—
NP-PA1004UL / NP-PA804UL		COMPUTER	—	—	—	—
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X		COMPUTER	—	—	—	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X		COMPUTER	BNC(CV)	BNC(Y/C)	—	—
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X		COMPUTER	BNC(CV)	BNC(Y/C)	—	USB-A
* NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U		COMPUTER1	VIDEO	S-VIDEO	HDMI	VIEWER
NP-PH3501QL / NP-PH2601QL		—	—	—	—	—
* NP-PH1400U		COMPUTER1	VIDEO	S-VIDEO	HDMI	VIEWER
NP-PH1202HL / NP-PH1002HL		COMPUTER	BNC(CV)	BNC(Y/C)	—	—
* NP-PH1000U		COMPUTER1	VIDEO	S-VIDEO	HDMI	VIEWER
NP-PX2000UL		COMPUTER	—	—	—	—
NP-PX1005QL		—	—	—	—	—
NP-PX1004UL NP-PX803UL		COMPUTER	BNC(CV)	BNC(Y/C)	—	—
* NP-PX750U / NP-PX700W / NP-PX800X		COMPUTER1	VIDEO	S-VIDEO	HDMI	VIEWER
NP-PX651X / NP-PX581W		Computer1	Video	S-Video	Component	—
* NP-PX620X / NP-PX550W		Computer1	Video	S-Video	Computer3	—
NP-PX602UL / NP-PX602WL		COMPUTER	BNC(CV)	BNC(Y/C)	—	—
NP-U321H		COMPUTER	VIDEO	—	HDMI1(078-3)	—
* NP-U300X / NP-U250X / NP-U310W / NP-U260W		COMPUTER1	VIDEO	S-VIDEO	HDMI	—
NP-UM352W		COMPUTER	VIDEO	—	—	—
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X		COMPUTER	VIDEO	—	—	USB-A
* NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W		COMPUTER	VIDEO	S-VIDEO	HDMI1	VIEWER
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H		COMPUTER	VIDEO	—	HDMI1(078-3)	—
* NP-V311W / NP-V281W / NP-V311X		COMPUTER1	VIDEO	S-VIDEO	HDMI	—
* NP-V300X / NP-V260X / NP-V300W / NP-V260W		COMPUTER1	VIDEO	S-VIDEO	HDMI	—
* NP-V230X / NP-V260 / NP-V230		COMPUTER	VIDEO	S-VIDEO	—	—
* NP-V260R		COMPUTER	VIDEO	S-VIDEO	HDMI	—
NP-VE303X / NP-VE303		COMPUTER	VIDEO	—	—	—
* NP-VE281X / NP-VE281		COMPUTER	VIDEO	—	HDMI	—
* NP-VE280X / NP-VE280		COMPUTER	VIDEO	—	—	—

Supplement for "305-3. BASIC INFORMATION REQUEST"

Parameter	Model name	Description
DATA04	Selection signal type 2 NP-U300X / NP-U250X / NP-U310W / NP-U260W	If there is no signal, FFh is returned.
DATA07	Sound mute NP-M420XV	FFh is returned.
DATA09	Freeze status NP4100 / NP4100W / NP-PX620X / NP-PX550W	Not supported (00h is always returned).

#### 4. Supplementary Information by Command

### 078-3. INPUT STATUS REQUEST 305-3. BASIC INFORMATION REQUEST

The asterisked models exclusively support "305-3. BASIC INFORMATION REQUEST".  
i.e. don't support "078-3. INPUT STATUS REQUEST".

#### ■ Selection signal type

Model name	DATA03	01h	01h	01h	01h
	DATA04	0Ah	20h	21h	22h
* NP4100 / NP4100W		—	—	—	—
NP-M420X / NP-M420XV NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS		—	—	—	—
* NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS		—	—	HDMI1	—
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS		—	—	HDMI1	—
* NP-M361W / NP-M311X / NP-M271X / NP-M311W / NP-M271W		—	—	—	—
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X		—	—	HDMI1	—
* NP-ME360X / NP-ME310X / NP-ME270X		—	—	—	—
NP-P603X / NP-P523X / NP-PE523X		—	—	HDMI1	—
NP-P54U / NP-P474U / NP-P54W / NP-P474W / NP-P604X		—	—	HDMI1	—
NP-P605UL / NP-P525UL / NP-P525WL		—	—	HDMI1	—
NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W		—	—	HDMI1	—
* NP-P501X / NP-P451X / NP-P451W / NP-P401W		—	—	—	—
* NP-P420X / NP-P350X / NP-P350W		—	—	—	—
* NP-PE501X		—	—	—	—
* NP-PE401H		—	—	—	—
NP-PA1004UL / NP-PA804UL		—	—	HDMI1	DiaplayPort
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X		—	—	HDMI1	DiaplayPort
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X		—	—	HDMI1	DiaplayPort
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X		—	—	HDMI1	DiaplayPort
* NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U		—	—	—	—
NP-PH3501QL / NP-PH2601QL		—	—	HDMI1	DiaplayPort1
* NP-PH1400U		STEREO DVI	—	—	—
NP-PH1202HL / NP-PH1002HL		—	—	HDMI	DiaplayPort
* NP-PH1000U		—	—	—	—
NP-PX2000UL		—	DVI-D	HDMI1	DiaplayPort
NP-PX1005QL		—	—	HDMI1	DiaplayPort1
NP-PX1004UL NP-PX803UL		—	—	HDMI	DiaplayPort
* NP-PX750U / NP-PX700W / NP-PX800X		—	—	—	—
NP-PX651X / NP-PX581W		—	—	—	Computer3
* NP-PX620X / NP-PX550W		—	—	—	—
NP-PX602UL / NP-PX602WL		—	—	HDMI	DiaplayPort
NP-U321H		—	—	HDMI1(305-3)	—
* NP-U300X / NP-U250X / NP-U310W / NP-U260W		—	—	—	—
NP-UM352W		—	—	HDMI1	—
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X		—	—	HDMI1	—
* NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W		—	—	—	—
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H		—	—	HDMI1(305-3)	—
* NP-V311W / NP-V281W / NP-V311X		—	—	—	—
* NP-V300X / NP-V260X / NP-V300W / NP-V260W		—	—	—	—
* NP-V230X / NP-V260 / NP-V230		—	—	—	—
* NP-V260R		—	—	—	—
NP-VE303X / NP-VE303		—	—	HDMI	—
* NP-VE281X / NP-VE281		—	—	—	—
* NP-VE280X / NP-VE280		—	—	—	—

Supplement for "305-3. BASIC INFORMATION REQUEST"

Parameter	Model name
DATA04 Selection signal type 2	NP-U300X / NP-U250X / NP-U310W / NP-U260W
DATA07 Sound mute	NP-M420XV
DATA09 Freeze status	NP4100 / NP4100W / NP-PX620X / NP-PX550W

#### 4. Supplementary Information by Command

##### 078-3. INPUT STATUS REQUEST 305-3. BASIC INFORMATION REQUEST

The asterisked models exclusively support "305-3. BASIC INFORMATION" i.e. don't support "078-3. INPUT STATUS REQUEST".

##### ■ Selection signal type

Model name	DATA03	01h	01h	01h	02h
	DATA04	23h	27h	28h	01h
* NP4100 / NP4100W		—	—	—	Computer2
NP-M420X / NP-M420XV		—	—	—	COMPUTER2
* NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS		—	—	—	COMPUTER2
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS		—	—	—	—
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS		—	—	—	—
* NP-M361W / NP-M311X / NP-M271X / NP-M311W / NP-M271W		—	—	—	COMPUTER2
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X		—	—	—	—
* NP-ME360X / NP-ME310X / NP-ME270X		—	—	—	COMPUTER2
NP-P603X / NP-P523X / NP-PE523X		—	—	—	—
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X		—	HDBaseT	—	—
NP-P605UL / NP-P525UL / NP-P525WL		—	HDBaseT	—	—
NP-P502HL / NP-P502WL		—	HDBaseT	—	—
NP-P502H / NP-P502W / NP-P452H / NP-P452W		—	HDBaseT	—	—
* NP-P501X / NP-P451X / NP-P451W / NP-P401W		—	—	—	—
* NP-P420X / NP-P350X / NP-P350W		—	—	—	COMPUTER2
* NP-PE501X		—	—	—	—
* NP-PE401H		—	—	—	—
NP-PA1004UL / NP-PA804UL		—	HDBaseT	—	—
NP-PA803UL / NP-PA653UL		—	HDBaseT	—	—
NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X		—	HDBaseT	—	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X		—	—	—	BNC
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X		—	—	—	BNC
* NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U		—	—	—	COMPUTER2
NP-PH3501QL / NP-PH2601QL		SLOT	HDBaseT	SDI1	—
* NP-PH1400U		—	—	—	COMPUTER2
NP-PH1202HL / NP-PH1002HL		SLOT	—	—	BNC
* NP-PH1000U		—	—	—	COMPUTER2
NP-PX2000UL		—	HDBaseT	SDI	BNC
NP-PX1005QL		SLOT	HDBaseT	SDI1	—
NP-PX1004UL		SLOT	HDBaseT	—	BNC
NP-PX803UL		SLOT	HDBaseT	—	BNC
* NP-PX750U / NP-PX700W / NP-PX800X		—	—	—	COMPUTER2
NP-PX651X / NP-PX581W		HDMI	—	—	—
* NP-PX620X / NP-PX550W		—	—	—	Computer2
NP-PX602UL / NP-PX602WL		SLOT	—	—	BNC
NP-U321H		—	—	—	—
* NP-U300X / NP-U250X / NP-U310W / NP-U260W		—	—	—	COMPUTER2
NP-UM352W		—	—	—	—
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X		—	—	—	—
* NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W		—	—	—	—
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H		—	—	—	—
* NP-V311W / NP-V281W / NP-V311X		—	—	—	COMPUTER2
* NP-V300X / NP-V260X / NP-V300W / NP-V260W		—	—	—	COMPUTER2
* NP-V230X / NP-V260 / NP-V230		—	—	—	—
* NP-V260R		—	—	—	—
NP-VE303X / NP-VE303		—	—	—	—
* NP-VE281X / NP-VE281		—	—	—	—
* NP-VE280X / NP-VE280		—	—	—	—

Supplement for "305-3. BASIC INFORMATION REQUEST"

Parameter	Model name
DATA04 Selection signal type 2	NP-U300X / NP-U250X / NP-U310W / NP-U260W
DATA07 Sound mute	NP-M420XV
DATA09 Freeze status	NP4100 / NP4100W / NP-PX620X / NP-PX550W

#### 4. Supplementary Information by Command

##### 078-3. INPUT STATUS REQUEST 305-3. BASIC INFORMATION REQUEST

The asterisked models exclusively support "305-3. BASIC INFORMATION REQUEST".  
i.e. don't support "078-3. INPUT STATUS REQUEST".

##### ■ Selection signal type

Model name	DATA03	02h	02h	02h	02h
	DATA04	06h	07h	21h	22h
* NP4100 / NP4100W		—	—	—	—
NP-M420X / NP-M420XV NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS		—	NETWORK	—	—
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS		—	LAN	HDMI2	—
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS		—	LAN	HDMI2	—
* NP-M361W / NP-M311X / NP-M271X / NP-M311W / NP-M271W		—	NETWORK	—	—
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X		—	LAN	HDMI2	—
* NP-ME360X / NP-ME310X / NP-ME270X		—	—	—	—
NP-P603X / NP-P523X / NP-PE523X		—	—	HDMI2	—
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X		—	—	HDMI2	—
NP-P605UL / NP-P525UL / NP-P525WL		—	LAN	HDMI2	—
NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W		—	—	HDMI2	—
* NP-P501X / NP-P451X / NP-P451W / NP-P401W		HDMI2	NETWORK	—	—
* NP-P420X / NP-P350X / NP-P350W		—	NETWORK	—	—
* NP-PE501X		HDMI2	—	—	—
* NP-PE401H		HDMI2	—	—	—
NP-PA1004UL / NP-PA804UL		—	—	HDMI2	—
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X		—	—	HDMI2	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X		—	HDBaseT	HDMI2	—
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X		—	ETHERNET	HDMI2	—
* NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U		DisplayPort	NETWORK	—	—
NP-PH3501QL / NP-PH2601QL		—	—	HDMI2	DiaplayPort2
* NP-PH1400U		DisplayPort	NETWORK	—	—
NP-PH1202HL / NP-PH1002HL		—	HDBaseT	—	—
* NP-PH1000U		DisplayPort	NETWORK	—	—
NP-PX2000UL		—	—	HDMI2	—
NP-PX1005QL		—	—	HDMI2	DiaplayPort2
NP-PX1004UL NP-PX803UL		—	—	—	—
* NP-PX750U / NP-PX700W / NP-PX800X		DisplayPort	NETWORK	—	—
NP-PX651X / NP-PX581W		Computer2	—	HDBaseT	—
* NP-PX620X / NP-PX550W		—	—	—	—
NP-PX602UL / NP-PX602WL		—	HDBaseT	—	—
NP-U321H		HDMI2(078-3)	—	HDMI2(305-3)	—
* NP-U300X / NP-U250X / NP-U310W / NP-U260W		—	—	—	—
NP-UM352W		—	—	HDMI2	—
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X		—	LAN	HDMI2	—
* NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W		HDMI2	NETWORK	—	—
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H		HDMI2(078-3)	—	HDMI2(305-3)	—
* NP-V311W / NP-V281W / NP-V311X		—	—	—	—
* NP-V300X / NP-V260X / NP-V300W / NP-V260W		—	—	—	—
* NP-V230X / NP-V260 / NP-V230		—	—	—	—
* NP-V260R		—	—	—	—
NP-VE303X / NP-VE303		—	—	—	—
* NP-VE281X / NP-VE281		—	—	—	—
* NP-VE280X / NP-VE280		—	—	—	—

Supplement for "305-3. BASIC INFORMATION REQUEST"

Parameter	Model name
DATA04 Selection signal type 2	NP-U300X / NP-U250X / NP-U310W / NP-U260W
DATA07 Sound mute	NP-M420XV
DATA09 Freeze status	NP4100 / NP4100W / NP-PX620X / NP-PX550W

#### 4. Supplementary Information by Command

##### 078-3. INPUT STATUS REQUEST 305-3. BASIC INFORMATION REQUEST

The asterisked models exclusively support "305-3. BASIC INFORMATION REQUEST".  
i.e. don't support "078-3. INPUT STATUS REQUEST".

##### ■ Selection signal type

Model name	DATA03	02h	03h	03h	03h
	DATA04	28h	01h	04h	06h
* NP4100 / NP4100W		—	—	Component	—
NP-M420X / NP-M420XV		—	—	—	—
* NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS		—	—	—	—
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS		—	—	—	—
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS		—	—	—	—
* NP-M361W / NP-M311X / NP-M271X / NP-M311W / NP-M271W		—	—	—	—
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X		—	—	—	—
* NP-ME360X / NP-ME310X / NP-ME270X		—	—	—	—
NP-P603X / NP-P523X / NP-PE523X		—	—	—	—
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X		—	—	—	—
NP-P605UL / NP-P525UL / NP-P525WL		—	—	—	—
NP-P502HL / NP-P502WL		—	—	—	—
NP-P502H / NP-P502W / NP-P452H / NP-P452W		—	—	—	—
* NP-P501X / NP-P451X / NP-P451W / NP-P401W		—	—	—	—
* NP-P420X / NP-P350X / NP-P350W		—	—	—	—
* NP-PE501X		—	—	—	—
* NP-PE401H		—	—	—	—
NP-PA1004UL / NP-PA804UL		—	—	—	—
NP-PA803UL / NP-PA653UL		—	—	—	—
NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X		—	—	—	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X		—	—	—	—
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X		—	—	—	—
* NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U		—	COMPUTER3	—	—
NP-PH3501QL / NP-PH2601QL		SDI2	—	—	—
* NP-PH1400U		—	COMPUTER3	—	SLOT
NP-PH1202HL / NP-PH1002HL		—	—	—	—
* NP-PH1000U		—	COMPUTER3	—	SLOT
NP-PX2000UL		—	—	—	—
NP-PX1005QL		SDI2	—	—	—
NP-PX1004UL		—	—	—	—
NP-PX803UL		—	—	—	—
* NP-PX750U / NP-PX700W / NP-PX800X		—	COMPUTER3	—	SLOT
NP-PX651X / NP-PX581W		—	—	—	—
* NP-PX620X / NP-PX550W		—	—	Component	—
NP-PX602UL / NP-PX602WL		—	—	—	—
NP-U321H		—	—	—	—
* NP-U300X / NP-U250X / NP-U310W / NP-U260W		—	—	—	—
NP-UM352W		—	—	—	—
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X		—	—	—	—
* NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W		—	—	—	—
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H		—	—	—	—
* NP-V311W / NP-V281W / NP-V311X		—	—	—	—
* NP-V300X / NP-V260X / NP-V300W / NP-V260W		—	—	—	—
* NP-V230X / NP-V260 / NP-V230		—	—	—	—
* NP-V260R		—	—	—	—
NP-VE303X / NP-VE303		—	—	—	—
* NP-VE281X / NP-VE281		—	—	—	—
* NP-VE280X / NP-VE280		—	—	—	—

Supplement for "305-3. BASIC INFORMATION REQUEST"

Parameter	Model name
DATA04 Selection signal type 2	NP-U300X / NP-U250X / NP-U310W / NP-U260W
DATA07 Sound mute	NP-M420XV
DATA09 Freeze status	NP4100 / NP4100W / NP-PX620X / NP-PX550W

## 4. Supplementary Information by Command

### 078-3. INPUT STATUS REQUEST 305-3. BASIC INFORMATION REQUEST

The asterisked models exclusively support "305-3. BASIC INFORMATION REQUEST".  
i.e. don't support "078-3. INPUT STATUS REQUEST".

#### ■ Selection signal type

Model name	DATA03	03h	04h	04h	05h
	DATA04	28h	07h	28h	07h
* NP4100 / NP4100W		—	—	—	—
NP-M420X / NP-M420XV NP-M350X / NP-M300X / NP-M260X / NP-M230X / NP-M300W / NP-M260W / NP-M350XS / NP-M300XS / NP-M260XS / NP-M300WS / NP-M260WS		—	USB DISPLAY	—	—
NP-M403X / NP-M363X / NP-M323X / NP-M283X / NP-M403W / NP-M363W / NP-M323W / NP-M333XS / NP-M353WS / NP-M303WS / NP-M403H / NP-M323H / NP-M353HS / NP-M323HS / NP-M303HS		—	USB-B	—	—
NP-M402W / NP-M362W / NP-M402X / NP-M362X / NP-M322X / NP-M282X / NP-M322W / NP-M352WS / NP-M302WS / NP-M332XS		—	USB-B	—	—
* NP-M361W / NP-M311X / NP-M271X / NP-M311W / NP-M271W		—	USB DISPLAY	—	—
NP-ME401W / NP-ME361W / NP-ME331W / NP-ME301W / NP-ME401X / NP-ME361X / NP-ME331X / NP-ME301X		—	USB-B	—	—
* NP-ME360X / NP-ME310X / NP-ME270X		—	—	—	—
NP-P603X / NP-P523X / NP-PE523X		—	—	—	—
NP-P554U / NP-P474U / NP-P554W / NP-P474W / NP-P604X		—	—	—	—
NP-P605UL / NP-P525UL / NP-P525WL		—	—	—	—
NP-P502HL / NP-P502WL NP-P502H / NP-P502W / NP-P452H / NP-P452W		—	—	—	APPS
* NP-P501X / NP-P451X / NP-P451W / NP-P401W		—	USB DISPLAY	—	—
* NP-P420X / NP-P350X / NP-P350W		—	USB DISPLAY	—	—
* NP-PE501X		—	USB DISPLAY	—	—
* NP-PE401H		—	—	—	—
NP-PA1004UL / NP-PA804UL		—	—	—	—
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X		—	—	—	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X		—	—	—	—
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X		—	—	—	—
* NP-PA600X / NP-PA500X / NP-PA550W / NP-PA500U		—	—	—	—
NP-PH3501QL / NP-PH2601QL		SDI3	—	SDI4	—
* NP-PH1400U		—	—	—	—
NP-PH1202HL / NP-PH1002HL		—	—	—	—
* NP-PH1000U		—	—	—	—
NP-PX2000UL		—	—	—	—
NP-PX1005QL		SDI3	—	SDI4	—
NP-PX1004UL NP-PX803UL		—	—	—	—
* NP-PX750U / NP-PX700W / NP-PX800X		—	—	—	—
NP-PX651X / NP-PX581W		—	—	—	—
* NP-PX620X / NP-PX550W		—	—	—	—
NP-PX602UL / NP-PX602WL		—	—	—	—
NP-U321H		—	—	—	—
* NP-U300X / NP-U250X / NP-U310W / NP-U260W		—	—	—	—
NP-UM352W		—	USB-B	—	APPS
NP-UM351W / NP-UM301W / NP-UM361X / NP-UM301X		—	USB-B	—	—
* NP-UM330X / NP-UM280X / NP-UM330W / NP-UM280W		—	USB DISPLAY	—	—
NP-V332X / NP-V332W / NP-V302X / NP-V302W / NP-V302H		—	—	—	—
* NP-V311W / NP-V281W / NP-V311X		—	—	—	—
* NP-V300X / NP-V260X / NP-V300W / NP-V260W		—	—	—	—
* NP-V230X / NP-V260 / NP-V230		—	—	—	—
* NP-V260R		—	—	—	—
NP-VE303X / NP-VE303		—	—	—	—
* NP-VE281X / NP-VE281		—	—	—	—
* NP-VE280X / NP-VE280		—	—	—	—

Supplement for "305-3. BASIC INFORMATION REQUEST"

Parameter	Model name
DATA04 Selection signal type 2	NP-U300X / NP-U250X / NP-U310W / NP-U260W
DATA07 Sound mute	NP-M420XV
DATA09 Freeze status	NP4100 / NP4100W / NP-PX620X / NP-PX550W

## 4. Supplementary Information by Command

### 097-198. PIP/PICTURE BY PICTURE REQUEST

### 098-198. PIP/PICTURE BY PICTURE SET

※ . . . SUB2 INPUT and SUB3 INPUT are not supported.

#### ■ Sub input

Model name	DATA02							
	00h	01h	02h	03h	04h	05h	06h	07h
NP-P605UL / NP-P525UL / NP-P525WL	OFF	—	—	HDMI1	HDMI2	—	COMPUTER	—
NP-PA1004UL / NP-PA804UL	OFF	—	—	HDMI1	HDMI2	DisplayPort	COMPUTER	—
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X	OFF	—	—	HDMI1	HDMI2	DisplayPort	COMPUTER	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X	OFF	BNC(CV)	BNC(Y/C)	HDMI1	HDMI2	DisplayPort	COMPUTER	BNC
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X	OFF	BNC(CV)	BNC(Y/C)	HDMI1	HDMI2	DisplayPort	COMPUTER	BNC
NP-PH3501QL / NP-PH2601QL	—	—	—	HDMI1	HDMI2	DisplayPort1	—	—
NP-PH1202HL / NP-PH1002HL	OFF	BNC(CV)	BNC(Y/C)	HDMI	SLOT	DisplayPort	COMPUTER	BNC
NP-PX1005QL	—	—	—	HDMI1	HDMI2	DisplayPort1	—	—
NP-PX1004UL NP-PX803UL	OFF	BNC(CV)	BNC(Y/C)	HDMI	SLOT	DisplayPort	COMPUTER	BNC
NP-PX602UL / NP-PX602WL	OFF	BNC(CV)	BNC(Y/C)	HDMI	SLOT	DisplayPort	COMPUTER	BNC

## 4. Supplementary Information by Co

### 097-198. PIP/PICTURE BY PICTURE REQUEST

### 098-198. PIP/PICTURE BY PICTURE SET

※ . . . SUB2 INPUT and SUB3 INPUT are not supported.

#### ■ Sub input

Model name	DATA02							
	08h	09h	0Ah	0Bh	0Ch	0Dh	0Eh	0Fh
NP-P605UL / NP-P525UL / NP-P525WL	HDBaseT	—	—	—	—	—	—	—
NP-PA1004UL / NP-PA804UL	HDBaseT	—	—	—	—	—	—	—
NP-PA803UL / NP-PA653UL NP-PA803U / NP-PA723U / NP-PA653U / NP-PA853W / NP-PA703W / NP-PA903X	HDBaseT	—	—	—	—	—	—	—
NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X	HDBaseT	—	—	—	—	—	—	—
NP-PA621U / NP-PA521U / NP-PA671W / NP-PA571W / NP-PA721X / NP-PA621X	ETHERNET	USB-A	—	—	—	—	—	—
NP-PH3501QL / NP-PH2601QL	HDBaseT※	—	DisplayPort2	SDI1	SDI2	SDI3	SDI4	SLOT※
NP-PH1202HL / NP-PH1002HL	HDBaseT	—	—	—	—	—	—	—
NP-PX1005QL	HDBaseT※	—	DisplayPort2	SDI1	SDI2	SDI3	SDI4	SLOT※
NP-PX1004UL NP-PX803UL	HDBaseT	—	—	—	—	—	—	—
NP-PX602UL / NP-PX602WL	HDBaseT	—	—	—	—	—	—	—

## 4. Supplementary Information by Command

### 319-10. AUDIO SELECT SET

#### ■ Audio select

Model name	DATA02						
	00h	01h	02h	03h	04h	05h	09h
NP-PA1004UL / NP-PA804UL / NP-PA622U / NP-PA522U / NP-PA672W / NP-PA572W / NP-PA722X / NP-PA622X	HDMI1	HDMI2	DisplayPort	HDBaseT	USB-A	USB-B	—
Other than the above models	HDMI1	HDMI2	DisplayPort	ETHRENET or LAN	USB-A	USB-B	HDBaseT